

FMB010 Teltonika Data Sending Parameters ID

[Main Page](#) > [Fast & Easy Trackers](#) > [FMB010](#) > **FMB010 Teltonika Data Sending Parameters ID**

Document updated according firmware FMB.Ver.03.18.18.Rev.50 and newer.

FMB AVL ID's consist of these **parameters groups**:

□

Contents

- [1 Permanent I/O elements](#)
- [2 Eventual I/O elements](#)
- [3 BLE Sensors I/O elements](#)

Permanent I/O elements

Property ID in AVL packet	Property Name	Bytes	Type	Value range		Multiplier	Units	Description	HW Support	Parameter Group
				Min	Max					

80

Data Mode

1

Unsign
ed

0

5

-

-

- 0 - Home On Stop
- 1 - Home On Moving
- 2 - Roaming On Stop
- 3 - Roaming On Moving
- 4 - Unknown On Stop
- 5 - Unknown On Moving

FMBXX
 X
 FMB00
 1
 FMC00
 1
 FMB01
 0
 FMB00
 2
 FMB02
 0
 FMB00
 3
 FMB11
 0
 FMB12
 0
 FMB12
 2
 FMB12
 5
 FMU12
 5
 FMB14
 0
 FMB15
 0
 FMC15
 0
 FMM1
 50
 FMB90
 0
 FMB92
 0
 FMB96
 2
 FMB96
 4
 FM300
 1
 FMB20
 2
 FMB20
 4
 FMB20
 6
 FMT10
 0
 MTB10
 0
 FMP10
 0
 MSP50
 0
 FMC80
 0
 FMM8
 00
 FMM8
 0A

Permanent I/O
Elements

21 GSM Signal 1 Unsigned 0 5 - - Value in range 1-5

FMBXX
X
FMB00
1
FMC00
1
FMB01
0
FMB00
2
FMB02
0
FMB00
3
FMB11
0
FMB12
0
FMB12
2
FMB12
5
FMU12
5
FMB14
0
FMB15
0
FMC15
0
FMM1 Permanent I/O
50 Elements
FMB90
0
FMB92
0
FMB96
2
FMB96
4
FM300
1
FMB20
2
FMB20
4
FMB20
6
FMT10
0
MTB10
0
FMP10
0
MSP50
0
FMC80
0
FMM8
00
FMM8
0A

200

Sleep Mode

1

Unsign
ed

0

4

-

-

- 0 - No Sleep
- 1 - GPS Sleep
- 2 - Deep Sleep
- 3 - Online Sleep
- 4 - Ultra Sleep

[FMBXX](#)
[X](#)
[FMB00](#)
[1](#)
[FMC00](#)
[1](#)
[FMB01](#)
[0](#)
[FMB00](#)
[2](#)
[FMB02](#)
[0](#)
[FMB00](#)
[3](#)
[FMB11](#)
[0](#)
[FMB12](#)
[0](#)
[FMB12](#)
[2](#)
[FMB12](#)
[5](#)
[FMU12](#)
[5](#)
[FMB14](#)
[0](#)
[FMB15](#)
[0](#)
[FMC15](#)
[0](#)
[FMM1](#)
[50](#)
[FMB90](#)
[0](#)
[FMB92](#)
[0](#)
[FMB96](#)
[2](#)
[FMB96](#)
[4](#)
[FM300](#)
[1](#)
[FMB20](#)
[2](#)
[FMB20](#)
[4](#)
[FMB20](#)
[6](#)
[FMT10](#)
[0](#)
[MTB10](#)
[0](#)
[FMP10](#)
[0](#)
[MSP50](#)
[0](#)
[FMC80](#)
[0](#)
[FMM8](#)
[00](#)
[FMM8](#)
[0A](#)

Permanent I/O
Elements

69

GNSS Status

1

Unsigned

0

3

-

-

- 0 - GNSS OFF
- 1 - GNSS ON with fix
- 2 - GNSS ON without fix
- 3 - GNSS sleep

FMBXX
 X
 FMB00
 1
 FMC00
 1
 FMB01
 0
 FMB00
 2
 FMB02
 0
 FMB00
 3
 FMB11
 0
 FMB12
 0
 FMB12
 2
 FMB12
 5
 FMU12
 5
 FMB14
 0
 FMB15
 0
 FMC15
 0
 FMM1
 50
 FMB90
 0
 FMB92
 0
 FMB96
 2
 FMB96
 4
 FM300
 1
 FMB20
 2
 FMB20
 4
 FMB20
 6
 FMT10
 0
 MTB10
 0
 FMP10
 0
 MSP50
 0
 FMC80
 0
 FMM8
 00
 FMM8
 0A

Permanent I/O Elements

66 External Voltage 2 Unsigned 0 65535 0.001 V Voltage

FMBXX
X
FMB00
1
FMC00
1
FMB01
0
FMB00
2
FMB02
0
FMB00
3
FMB11
0
FMB12
0
FMB12
2
FMB12
5
FMB13
0
FMB14
0
FMB15
0
FMC15
0
FMM1
50
FMU12
5
FMB90
0
FMB92
0
FMB96
2
FMB96
4
FM300
1
FMB20
2
FMB20
4
FMB20
6
FMT10
0
MTB10
0
FMP10
0
MSP50
0
FMC80
0
FMM8
00
FMM8
0A

Permanent I/O
elements

24 Speed 2 Unsigned 0 350 - km/h GNSS Speed

FMBXX
X
FMB00
1
FMC00
1
FMB01
0
FMB00
2
FMB02
0
FMB00
3
FMB11
0
FMB12
0
FMB12
2
FMB12
5
FMU12
5
FMB14
0
FMB15
0
FMC15
0
FMM1 Permanent I/O
50 elements
FMB90
0
FMB92
0
FMB96
2
FMB96
4
FM300
1
FMB20
2
FMB20
4
FMB20
6
FMT10
0
MTB10
0
FMP10
0
MSP50
0
FMC80
0
FMM8
00
FMM8
0A

205 GSM Cell ID 2 Unsigned 0 65535 - - GSM base station ID

FMBXX
X
FMB00
1
FMC00
1
FMB01
0
FMB00
2
FMB02
0
FMB00
3
FMB11
0
FMB12
0
FMB12
2
FMB12
5
FMU12
5
FMB14
0
FMB15
0
FMC15
0
FMM1 Permanent I/O
50 elements
FMB90
0
FMB92
0
FMB96
2
FMB96
4
FM300
1
FMB20
2
FMB20
4
FMB20
6
FMT10
0
MTB10
0
FMP10
0
MSP50
0
FMC80
0
FMM8
00
FMM8
0A

67 Battery Voltage 2 Unsigned 0 65535 0.001 V Voltage

FMBXX
X
FMB00
1
FMC00
1
FMB01
0
FMB12
0
FMB12
2
FMB12
5
FMB13
0
FMB14
0
FMB15
0
FMC15
0
FMM1
50
FMB92
0
FMB96
2
FMB96
4
FM300
1
FMB20
2
FMB20
4
FMB20
6
FMT10
0
MTB10
0
FMC80
0
FMM8
00
FMM8
0A

Permanent I/O
elements

68 Battery Current 2 Unsigned 0 65535 0.001 A Current

FMBXX
X
FMB00
1
FMC00
1
FMB01
0
FMB12
0
FMB12
2
FMB12
5
FMU12
5
FMC12
5
FMM1
25
FMB13
0
FMU13
0
FMC13
0
FMM1
30
FMB92
0
FMB96
2
FMB96
4
FM300
1
FMB20
2
FMB20
4
FMB20
6
FMT10
0
MTB10
0
FMB14
0
FMC80
0
FMM8
00
FMM8
0A

Permanent I/O
elements

16 Total Odometer 4 Unsign 0 21474 - - Total Odometer value in meters

FMBXX
X
FMB00
1
FMC00
1
FMB01
0
FMB00
2
FMB02
0
FMB00
3
FMB11
0
FMB12
0
FMB12
2
FMB12
5
FMU12
5
FMB14
0
FMB15
0
FMC15
0
FMM1 Permanent I/O
50 elements
FMB90
0
FMB92
0
FMB96
2
FMB96
4
FM300
1
FMB20
2
FMB20
4
FMB20
6
FMT10
0
MTB10
0
FMP10
0
MSP50
0
FMC80
0
FMM8
00
FMM8
0A

9 Analog Input 1 2 Unsigned 0 65535 0.001 mV Voltage

FMBXX
X
[FMB00](#)
[1](#)
[FMB01](#)
[0](#)
[FMB11](#)
[0](#)
[FMB12](#)
[0](#)
[FMB12](#)
[2](#)
[FMB12](#)
[5](#)
[FMU12](#)
[5](#)
[FMC12](#)
[5](#)
[FMM1](#)
[25](#)
[FMB13](#)
[0](#)
[FMB13](#) Permanent I/O
[0](#) elements
[FMM1](#)
[30](#)
[FMB14](#)
[0](#)
[FMB90](#)
[0](#)
[FMB92](#)
[0](#)
[FMB96](#)
[2](#)
[FMB96](#)
[4](#)
[FMB20](#)
[2](#)
[FMB20](#)
[4](#)
[FMB20](#)
[6](#)
[MTB10](#)
[0](#)

179 Digital Output 1 1 Unsigned 0 1 - - Logic: 0/1

FMBXX
X
[FMB11](#)
0
[FMB12](#)
0
[FMB12](#)
2
[FMB12](#)
5
[FMU12](#)
5
[FMC12](#)
5
[FMM1](#)
25
[FMB13](#)
0
[FMU13](#)
0
[FMC13](#)
0
[FMM1](#)
30
[FMB14](#)
0
[FMB15](#)
0
[FMC15](#)
0
[FMM1](#)
50
[FMB90](#)
0
[FMB92](#)
0
[FMB96](#)
2
[FMB96](#)
4
[FMB20](#)
2
[FMB20](#)
4
[FMB20](#)
6
[MTB10](#)
0

Permanent I/O
elements

12 Fuel Used GPS 4 Unsigned 0 42949 0.001 1 Fuel Used
67295

FMBXX
X
FMB00
1
FMC00
1
FMB01
0
FMB11
0
FMB12
0
FMB12
2
FMB12
5
FMU12
5
FMC12
5
FMM1
25
FMB13
0
FMU13
0
FMC13
0
FMM1 Permanent I/O
30 elements
FMB14
0
FMB90
0
FMB92
0
FMB96
2
FMB96
4
FM300
1
FMB20
2
FMB20
4
FMB20
6
FMT10
0
MTB10
0
FMC80
0
FMM8
00
FMM8
0A

17 Axis X 2 Signed -8000 8000 - mG X axis value

FMBXX
X
FMB00
1
FMC00
1
FMB01
0
FMB00
2
FMB02
0
FMB00
3
FMB11
0
FMB12
0
FMB12
2
FMB12
5
FMU12
5
FMB14
0
FMB15
0
FMC15
0
FMM1 Permanent I/O
50 elements
FMB90
0
FMB92
0
FMB96
2
FMB96
4
FM300
1
FMB20
2
FMB20
4
FMB20
6
FMT10
0
MTB10
0
FMP10
0
MSP50
0
FMC80
0
FMM8
00
FMM8
0A

18 Axis Y 2 Signed -8000 8000 - mG Y axis value

FMBXX
X
FMB00
1
FMC00
1
FMB01
0
FMB00
2
FMB02
0
FMB00
3
FMB11
0
FMB12
0
FMB12
2
FMB12
5
FMU12
5
FMB14
0
FMB15
0
FMC15
0
FMM1 Permanent I/O
50 elements
FMB90
0
FMB92
0
FMB96
2
FMB96
4
FM300
1
FMB20
2
FMB20
4
FMB20
6
FMT10
0
MTB10
0
FMP10
0
MSP50
0
FMC80
0
FMM8
00
FMM8
0A

19 Axis Z 2 Signed -8000 8000 - mG Z axis value

FMBXX
X
FMB00
1
FMC00
1
FMB01
0
FMB00
2
FMB02
0
FMB00
3
FMB11
0
FMB12
0
FMB12
2
FMB12
5
FMU12
5
FMB14
0
FMB15
0
FMC15
0
FMM1 Permanent I/O
50 elements
FMB90
0
FMB92
0
FMB96
2
FMB96
4
FM300
1
FMB20
2
FMB20
4
FMB20
6
FMT10
0
MTB10
0
FMP10
0
MSP50
0
FMC80
0
FMM8
00
FMM8
0A

10 SD Status 1 Unsigned 0 1 - - 0 - not present 1 - present

FMBXX
X
[FMB00](#)
[1](#)
[FMB01](#)
[0](#)
[FMB11](#)
[0](#)
[FMB12](#)
[0](#)
[FMB12](#)
[2](#)
[FMB12](#)
[5](#)
[FMB12](#)
[5](#)
[FMC12](#)
[5](#)
[FMB13](#)
[0](#)
[FMB13](#) Permanent I/O
[0](#) elements
[FMB90](#)
[0](#)
[FMB92](#)
[0](#)
[FMB96](#)
[2](#)
[FMB96](#)
[4](#)
[FM300](#)
[1](#)
[FMB20](#)
[2](#)
[FMB20](#)
[4](#)
[FMB20](#)
[6](#)
[FMT10](#)
[0](#)

6	Analog Input 2	2	Unsigned	0	65535	0.001	mV	Voltage	FMBXX X FMB11 0 FMB12 0 FMB12 2 FMB13 0 FMU13 0 FMC13 0 FMM1 30 FMB14 0 FMBXX X FMB11 0 FMB12 0 FMB12 2 FMB13 0 FMU13 0 FMC13 0 FMM1 30 FMB14 0	Permanent I/O elements
180	Digital Output 2	1	Unsigned	0	1	-	-	Logic 0/1	FMM1 30 FMB14 0 FMB15 0 FMC15 0 FMM1 50 FMB20 2 FMB20 4 FMB20 6 FMBXX X FMB11 0 FMB12 0 FMB12 2 FMB12 5 FMU12 5 FMC12 5 FMM1 25 FMB13 0 FMB14 0 FMB15 0 FMC15 0 FMM1 50 FMU13 0 FMC13 0 FMM1 30 FMB20 2 FMB20 4 FMB20 6	Permanent I/O elements
72	Dallas Temperature 1	4	Signed	-550	1150	0.1	°C	Degrees (°C), -55 - +115, if 850 - Sensor not ready if 2000 - Value read error if 3000 - Not connected if 4000 - ID failed if 5000 - same as 850	FMB13 0 FMB14 0 FMB15 0 FMC15 0 FMM1 50 FMU13 0 FMC13 0 FMM1 30 FMB20 2 FMB20 4 FMB20 6	Permanent I/O elements

73	Dallas Temperature 2	4	Signed	-550	1150	0.1	°C	Degrees (°C), -55 - +115, if 850 - Sensor not ready if 2000 - Value read error if 3000 - Not connected if 4000 - ID failed if 5000 - same as 850	FMBXX X FMB11 0 FMB12 0 FMB12 2 FMB12 5 FMU12 5 FMC12 5 FMM1 25 FMB13 0 FMB14 0 FMB15 0 FMC15 0 FMM1 50 FMU13 0 FMC13 0 FMM1 30 FMB20 2 FMB20 4 FMB20 6 FMBXX X FMB11 0 FMB12 0 FMB12 2 FMB12 5 FMU12 5 FMC12 5 FMM1 25 FMB13 0 FMB14 0 FMB15 0 FMC15 0 FMM1 50 FMU13 0 FMC13 0 FMM1 30 FMB20 2 FMB20 4 FMB20 6	Permanent I/O elements
74	Dallas Temperature 3	4	Signed	-550	1150	0.1	°C	Degrees (°C), -55 - +115, if 850 - Sensor not ready if 2000 - Value read error if 3000 - Not connected if 4000 - ID failed if 5000 - same as 850	FMBXX X FMB11 0 FMB12 0 FMB12 2 FMB12 5 FMU12 5 FMC12 5 FMM1 25 FMB13 0 FMB14 0 FMB15 0 FMC15 0 FMM1 50 FMU13 0 FMC13 0 FMM1 30 FMB20 2 FMB20 4 FMB20 6	Permanent I/O elements

75	Dallas Temperature	4	4	Signed	-550	1150	0.1	°C	Degrees (°C), -55 - +115, if 850 - Sensor not ready if 2000 - Value read error if 3000 - Not connected if 4000 - ID failed if 5000 - same as 850	FMBXX X FMB11 0 FMB12 0 FMB12 2 FMB12 5 FMB12 5 FMC12 5 FMM1 25 FMB13 0 FMB14 0 FMB15 0 FMC15 0 FMM1 50 FMU13 0 FMC13 0 FMM1 30 FMB20 2 FMB20 4 FMB20 6 FMBXX X FMB11 0 FMB12 0 FMB12 2 FMB12 5 FMU12 5 FMC12 5 FMM1 25 FMB13 0 FMB14 0 FMB15 0 FMC15 0 FMM1 50 FMU13 0 FMC13 0 FMM1 30 FMB20 2 FMB20 4 FMB20 6	Permanent I/O elements
76	Dallas Temperature ID	1	8	Unsigned	0	0xffffffff	-	-	Dallas sensor ID	FMBXX X FMB11 0 FMB12 0 FMB12 2 FMB12 5 FMU12 5 FMC12 5 FMM1 25 FMB13 0 FMB14 0 FMB15 0 FMC15 0 FMM1 50 FMU13 0 FMC13 0 FMM1 30 FMB20 2 FMB20 4 FMB20 6	Permanent I/O elements

201	LLS 1 Fuel Level	2	Signed	-4	32767	-	kvants or ltr	Fuel level measured by LLS sensor via RS232/RS485	FMB12 5 FMB12 5 FMU12 5 FMC12 5 FMM1 25 FMB12 5 FMB12 5	Permanent I/O elements
202	LLS 1 Temperature	1	Signed	-128	127	-	°C	Fuel temperature measured by LLS via RS232/RS485	FMU12 5 FMC12 5 FMM1 25 FMB12 5 FMB12 5	Permanent I/O elements
203	LLS 2 Fuel Level	2	Signed	-4	32767	-	kvants or ltr	Fuel level measured by LLS sensor via RS485	FMU12 5 FMC12 5 FMM1 25 FMB12 5 FMB12 5	Permanent I/O elements
204	LLS 2 Temperature	1	Signed	-128	127	-	°C	Fuel temperature measured by LLS via RS485	FMU12 5 FMC12 5 FMM1 25 FMB12 5 FMB12 5	Permanent I/O elements
210	LLS 3 Fuel Level	2	Unsign ed	-4	32767	-	kvants or ltr	Fuel level measured by LLS sensor via RS485	FMU12 5 FMC12 5 FMM1 25 FMB12 5 FMB12 5	Permanent I/O elements
211	LLS 3 Temperature	1	Signed	-128	127	-	°C	Fuel temperature measured by LLS via RS485	FMU12 5 FMC12 5 FMM1 25 FMB12 5 FMB12 5	Permanent I/O elements
212	LLS 4 Fuel Level	2	Signed	-4	32767	-	kvants or ltr	Fuel level measured by LLS sensor via RS485	FMU12 5 FMC12 5 FMM1 25 FMB12 5 FMB12 5	Permanent I/O elements
213	LLS 4 Temperature	1	Signed	-128	127	-	°C	Fuel temperature measured by LLS via RS485	FMU12 5 FMC12 5 FMM1 25	Permanent I/O elements

214	LLS 5 Fuel Level	2	Signed	-4	32767	-	kvants or ltr	Fuel level measured by LLS sensor via RS485	FMB12 5 FMB12 5 FMU12 5 FMC12 5 FMM1 25 FMB12 5 FMB12 5 FMU12 5 FMC12 5 FMM1 25	Permanent I/O elements
215	LLS 5 Temperature	1	Signed	-128	127	-	°C	Fuel temperature measured by LLS via RS485	FMBXX X FMB00 1 FMC00 1 FMB01 0 FMB11 0 FMB12 0 FMB12 2 FMB12 5 FMU12 5 FMC12 5 FMM1 25 FMB13 0 FMU13 0 FMC13 0 FMM1 30 FMB14 0	Permanent I/O elements
15	Eco Score	2	Unsign ed	0	65535	0.01	-	Average amount of events on some distance	FMB15 0 FMC15 0 FMM1 50 FMB90 0 FMB92 0 FMB96 2 FMB96 4 FM300 1 FMB20 2 FMB20 4 FMB20 6 FMT10 0 MTB10 0 FMC80 0 FMM8 00 FMM8 0A	Permanent I/O elements

113	Battery Level	1	Unsigned	0	100	-	%	Battery capacity level	FMBXX X FMB00 1 FMC00 1 FMB01 0 FMB12 0 FMB12 2 FMB12 5 FMB13 0 FMB14 0 FMB15 0 FMC15 0 FMM1 50 FMB92 0 FMB96 2 FMB96 4 FM300 1 FMB20 2 FMB20 4 FMB20 6 FMT10 0 MTB10 0 FMC80 0 FMM8 00 FMM8 0A	Permanent I/O elements
-----	---------------	---	----------	---	-----	---	---	------------------------	--	------------------------

238	User ID	8	Unsigned	0	0xffffffff ffffffff	-	-	MAC address of NMEA receiver device connected via Bluetooth	FMBXX X FMB00 1 FMC00 1 FMB01 0 FMB11 0 FMB12 0 FMB12 2 FMB12 5 FMB13 0 FMB14 0 FMB15 0 FMC15 0 FMM1 50 FMB90 0 FMB92 0 FMB20 2 FMB20 4 FMB20 6 FMT10 0 FMP10 0 FMC00 1 FMC12 5 FMC13 0 FMC92 0 FMM0 01 FMM1 25 FMM1 30 FMC80 0 FMM8 00 FMM8 0A FMC88 0 FMM8 80 FMM9 20 FMC25 0	Permanent I/O elements
-----	---------	---	----------	---	------------------------	---	---	---	--	------------------------

237	Network Type	1	Unsigned	0	1	-	-	0 - 3G 1 - GSM 2 - 4G 3 - LTE CAT M1 4 - LTE CAT NB1 99 - Unknown	FM300 1 FMU12 5 FMU12 6 FMU13 0 FMC12 5 FMC13 0 FMC15 0 FMM1 25 FMM1 30 FMM1 50 FMC00 1 FMM0 01 FMC80 0 FMM8 00 FMC88 0 FMM8 80 FMM8 0A FMB11 0 FMB12 0	Permanent I/O elements
8	Authorized iButton	8	Unsigned	0	0xffffffff	-	-	If ID is shown in this I/O that means that attached iButton is in iButton List	FMB12 0 FMB12 2 FMB12 5 FMBXX X FMB11 0 FMB12 0 FMB12 2 FMB12 5 FMB12 5	Permanent I/O elements
4	Pulse Counter Din1	4	Unsigned	0	4294967295	-	-	Counts pulses, count is reset when records are saved	FMB12 5 FMC12 5 FMM1 25 FMB13 0 FMU13 0 FMC13 0 FMM1 30 FMBXX X FMB11 0 FMB12 0 FMB12 2	Permanent I/O elements
5	Pulse Counter Din2	4	Unsigned	0	4294967295	-	-	Counts pulses, count is reset when records are saved	FMB12 2 FMB13 0 FMU13 0 FMC13 0 FMM1 30	Permanent I/O elements

263	BT Status	1	Unsigned	0	4	-	-	<p>0 - BT is disabled 1 - BT Enabled, not device connected 2 - Device connected, BTv3 Only 3 - Device connected, BLE only 4 - Device connected, BLE + BT</p>	<p>FMBXX X FMB00 1 FMC00 1 FMB01 0 FMB11 0 FMB12 0 FMB12 2 FMB12 5 FMU12 5 FMC12 5 FMM1 25 FMB13 0 FMU13 0 FMC13 0 FMM1 30 FMB14 0 FMB15 0 FMC15 0 FMM1 50 FMB90 0 FMB92 0 FMB96 2 FMB96 4 FM300 1 FMB20 2 FMB20 4 FMB20 6 FMT10 0 MTB10 0 FMC80 0 FMM8 00 FMM8 0A</p>	Permanent I/O elements
-----	-----------	---	----------	---	---	---	---	---	---	------------------------

										FMBXX X FMB00 1 FMB01 0 FMB11 0 FMB12 0 FMB12 2 FMB12 5 FMU12 5 FMC12 5 FMM1 25 FMB13 0 FMU13 0 FMC13 0 FMM1 30	
264	Barcode ID	Variable	ASCII	0	32	-	-	Barcode ID		FMB14 0 FMB15 0 FMC15 0 FMM1 50 FMB90 0 FMB92 0 FMB96 2 FMB96 4 FM300 1 FMB20 2 FMB20 4 FMB20 6 FMT10 0 MTB10 0 FMB12 5 FMB12 5 FMU12 5 FMC12 5 FMM1 25 FMB12 5 FMB12 5 FMU12 5 FMC12 5 FMM1 25	Permanent I/O elements
269	Escort LLS Temperature #1	2	Signed	-128	127	-	°C	Fuel temperature		FMT10 0 MTB10 0 FMB12 5 FMB12 5 FMU12 5 FMC12 5 FMM1 25 FMB12 5 FMB12 5 FMU12 5 FMC12 5 FMM1 25	Permanent I/O elements
270	Escort LLS Fuel level #1	2	Unsigned	0	65535	-	-	Fuel Level		FMB12 5 FMB12 5 FMU12 5 FMC12 5 FMM1 25 FMB12 5 FMB12 5 FMU12 5 FMC12 5 FMM1 25	Permanent I/O elements
271	Escort LLS Battery Voltage #1	2	Unsigned	0	65535	0.01	V	Battery Voltage		FMB12 5 FMB12 5 FMU12 5 FMC12 5 FMM1 25	Permanent I/O elements

272	Escort LLS Temperature #2	2	Signed	-128	127	-	°C	Fuel temperature	FMB125 FMB125 FMU125 FMC125 FMM125 FMB125 FMB125	Permanent I/O elements
273	Escort LLS Fuel level #2	2	Unsigned	0	65535	-	-	Fuel Level	FMU125 FMC125 FMM125 FMB125 FMB125	Permanent I/O elements
274	Escort LLS Battery Voltage #2	2	Unsigned	0	65535	0.01	V	Battery Voltage	FMU125 FMC125 FMM125 FMB125 FMB125	Permanent I/O elements
275	Escort LLS Temperature #3	2	Signed	-128	127	-	°C	Fuel temperature	FMU125 FMC125 FMM125 FMB125 FMB125	Permanent I/O elements
276	Escort LLS Fuel level #3	2	Unsigned	0	65535	-	-	Fuel Level	FMU125 FMC125 FMM125 FMB125 FMB125	Permanent I/O elements
277	Escort LLS Battery Voltage #3	2	Unsigned	0	65535	0.01	V	Battery Voltage	FMU125 FMC125 FMM125 FMB125 FMB125	Permanent I/O elements
278	Escort LLS Temperature #4	2	Signed	-128	127	-	°C	Fuel temperature	FMU125 FMC125 FMM125 FMB125 FMB125	Permanent I/O elements
279	Escort LLS Fuel level #4	2	Unsigned	0	65535	-	-	Fuel Level	FMU125 FMC125 FMM125	Permanent I/O elements

280	Escort LLS Battery Voltage #4	2	Unsigned	0	65535	0.01	V	Battery Voltage	FMB125 FMB125 FMU125 FMC125 FMM125 FMBXX X FMB001 FMC001 FMB010 FMB110 FMB120 FMB122 FMB125 FMU125 FMC125 FMM125 FMB130 FMU130 FMC130	Permanent I/O elements
303	Instant Movement	1	Unsigned	0	1	-	-	Logic: 0/1 returns movement value	FMM130 FMB140 FMB150 FMC150 FMM150 FMB900 FMB920 FMB962 FMB964 FM3001 FMB202 FMB204 FMB206 FMT100 MTB100 FMB125 FMB125	Permanent I/O elements
327	UL202-02 Sensor Fuel level	2	Signed	-150	32767	0.1	mm	UL202-02 Sensor Fuel level	FMU125 FMC125 FMM125	Permanent I/O elements

483	UL202-02 Sensor Status	1	Unsigned	0	255	-	-	UL202-02 sensor status codes	FMB125 FMB125 FMC125 FMM125 FMBXX X FMB130 FMU130	Permanent I/O elements
380	Digital output 3	1	Unsigned	0	1	-	-	Logic: 0/1	FMC130 FMC150 FMM130 FMB130 FMU130	Permanent I/O elements
381	Ground Sense	1	Unsigned	0	1	-	-	Logic: 0/1	FMC130 FMM130 FMB140	Permanent I/O elements

387	ISO6709 Coordinates	34	HEX	0	0x7fffff fffffff	-	-	ISO6709 Coordinates Latitude, Longitude (in Degrees, Minutes and Seconds) and Altitude: IO value format: ±DDMMSS.SSSS±DDMMSS.SSSS±AAA.AAA/	FMBXX X FMB00 1 FMC00 1 FMB01 0 FMB00 2 FMB02 0 FMB00 3 FMB11 0 FMB12 0 FMB12 2 FMB12 5 FMU12 5 FMC12 5 FMB13 0 FMU13 0 FMC13 0 FMB14 0 FMB15 0 FMC15 0 FMM1 50 FMB90 0 FMB92 0 FMB91 0 FMB96 2 FMB96 4 FM300 1 FMB20 2 FMB20 4 FMB20 6 FMT10 0 MTB10 0 FMP10 0 FMB14 0 MSP50 0 FMC80 0 FMM8 00 FMM8 0A	Permanent I/O elements
-----	---------------------	----	-----	---	---------------------	---	---	--	--	---------------------------

217	Confidence zone 36	1	Unassigned	0	3	-	-	<ul style="list-style-type: none"> 0 - target left zone 1 - target entered zone 2 - over spending end 3 - over spending start 	FM5XXX 216000 216001 216002 216003 216004 216005 216006 216007 216008 216009 216010 216011 216012 216013 216014 216015 216016 216017 216018 216019 216020 216021 216022 216023 216024 216025 216026 216027 216028 216029 216030 216031 216032 216033 216034 216035 216036 216037 216038 216039 216040 216041 216042 216043 216044 216045 216046 216047 216048 216049 216050 216051 216052 216053 216054 216055 216056 216057 216058 216059 216060 216061 216062 216063 216064 216065 216066 216067 216068 216069 216070 216071 216072 216073 216074 216075 216076 216077 216078 216079 216080 216081 216082 216083 216084 216085 216086 216087 216088 216089 216090 216091 216092 216093 216094 216095 216096 216097 216098 216099 216100 216101 216102 216103 216104 216105 216106 216107 216108 216109 216110 216111 216112 216113 216114 216115 216116 216117 216118 216119 216120 216121 216122 216123 216124 216125 216126 216127 216128 216129 216130 216131 216132 216133 216134 216135 216136 216137 216138 216139 216140 216141 216142 216143 216144 216145 216146 216147 216148 216149 216150 216151 216152 216153 216154 216155 216156 216157 216158 216159 216160 216161 216162 216163 216164 216165 216166 216167 216168 216169 216170 216171 216172 216173 216174 216175 216176 216177 216178 216179 216180 216181 216182 216183 216184 216185 216186 216187 216188 216189 216190 216191 216192 216193 216194 216195 216196 216197 216198 216199 216200 216201 216202 216203 216204 216205 216206 216207 216208 216209 216210 216211 216212 216213 216214 216215 216216 216217 216218 216219 216220 216221 216222 216223 216224 216225 216226 216227 216228 216229 216230 216231 216232 216233 216234 216235 216236 216237 216238 216239 216240 216241 216242 216243 216244 216245 216246 216247 216248 216249 216250 216251 216252 216253 216254 216255 216256 216257 216258 216259 216260 216261 216262 216263 216264 216265 216266 216267 216268 216269 216270 216271 216272 216273 216274 216275 216276 216277 216278 216279 216280 216281 216282 216283 216284 216285 216286 216287 216288 216289 216290 216291 216292 216293 216294 216295 216296 216297 216298 216299 216300 216301 216302 216303 216304 216305 216306 216307 216308 216309 216310 216311 216312 216313 216314 216315 216316 216317 216318 216319 216320 216321 216322 216323 216324 216325 216326 216327 216328 216329 216330 216331 216332 216333 216334 216335 216336 216337 216338 216339 216340 216341 216342 216343 216344 216345 216346 216347 216348 216349 216350 216351 216352 216353 216354 216355 216356 216357 216358 216359 216360 216361 216362 216363 216364 216365 216366 216367 216368 216369 216370 216371 216372 216373 216374 216375 216376 216377 216378 216379 216380 216381 216382 216383 216384 216385 216386 216387 216388 216389 216390 216391 216392 216393 216394 216395 216396 216397 216398 216399 216400 216401 216402 216403 216404 216405 216406 216407 216408 216409 216410 216411 216412 216413 216414 216415 216416 216417 216418 216419 216420 216421 216422 216423 216424 216425 216426 216427 216428 216429 216430 216431 216432 216433 216434 216435 216436 216437 216438 216439 216440 216441 216442 216443 216444 216445 216446 216447 216448 216449 216450 216451 216452 216453 216454 216455 216456 216457 216458 216459 216460 216461 216462 216463 216464 216465 216466 216467 216468 216469 216470 216471 216472 216473 216474 216475 216476 216477 216478 216479 216480 216481 216482 216483 216484 216485 216486 216487 216488 216489 216490 216491 216492 216493 216494 216495 216496 216497 216498 216499 216500 216501 216502 216503 216504 216505 216506 216507 216508 216509 216510 216511 216512 216513 216514 216515 216516 216517 216518 216519 216520 216521 216522 216523 216524 216525 216526 216527 216528 216529 216530 216531 216532 216533 216534 216535 216536 216537 216538 216539 216540 216541 216542 216543 216544 216545 216546 216547 216548 216549 216550 216551 216552 216553 216554 216555 216556 216557 216558 216559 216560 216561 216562 216563 216564 216565 216566 216567 216568 216569 216570 216571 216572 216573 216574 216575 216576 216577 216578 216579 216580 216581 216582 216583 216584 216585 216586 216587 216588 216589 216590 216591 216592 216593 216594 216595 216596 216597 216598 216599 216600 216601 216602 216603 216604 216605 216606 216607 216608 216609 216610 216611 216612 216613 216614 216615 216616 216617 216618 216619 216620 216621 216622 216623 216624 216625 216626 216627 216628 216629 216630 216631 216632 216633 216634 216635 216636 216637 216638 216639 216640 216641 216642 216643 216644 216645 216646 216647 216648 216649 216650 216651 216652 216653 216654 216655 216656 216657 216658 216659 216660 216661 216662 216663 216664 216665 216666 216667 216668 216669 216670 216671 216672 216673 216674 216675 216676 216677 216678 216679 216680 216681 216682 216683 216684 216685 216686 216687 216688 216689 216690 216691 216692 216693 216694 216695 216696 216697 216698 216699 216700 216701 216702 216703 216704 216705 216706 216707 216708 216709 216710 216711 216712 216713 216714 216715 216716 216717 216718 216719 216720 216721 216722 216723 216724 216725 216726 216727 216728 216729 216730 216731 216732 216733 216734 216735 216736 216737 216738 216739 216740 216741 216742 216743 216744 216745 216746 216747 216748 216749 216750 216751 216752 216753 216754 216755 216756 216757 216758 216759 216760 216761 216762 216763 216764 216765 216766 216767 216768 216769 216770 216771 216772 216773 216774 216775 216776 216777 216778 216779 216780 216781 216782 216783 216784 216785 216786 216787 216788 216789 216790 216791 216792 216793 216794 216795 216796 216797 216798 216799 216800 216801 216802 216803 216804 216805 216806 216807 216808 216809 216810 216811 216812 21681
-----	--------------------	---	------------	---	---	---	---	---	--

385 Beacon Variable HEX 0 1024 - - List of Beacon IDs

FMBX
XX
[FMB0](#)
[01](#)
[FMC0](#)
[01](#)
[FMB0](#)
[10](#)
[FMB0](#)
[02](#)
[FMB0](#)
[20](#)
[FMB0](#)
[03](#)
[FMB1](#)
[10](#)
[FMB1](#)
[20](#)
[FMB1](#)
[22](#)
[FMB1](#)
[25](#)
[FMU1](#)
[25](#)
[FMC1](#)
[25](#)
[FMB1](#)
[30](#)
[FMU1](#)
[30](#)
[FMC1](#)
[30](#)
[FMB1](#)
[40](#)
[FMB1](#)
[50](#) Permanent
[FMC1](#) I/O elements
[50](#)
[FMM](#)
[150](#)
[FMB9](#)
[00](#)
[FMB9](#)
[20](#)
[FMB9](#)
[10](#)
[FMB9](#)
[62](#)
[FMB9](#)
[64](#)
[FM30](#)
[01](#)
[FMB2](#)
[02](#)
[FMB2](#)
[04](#)
[FMB2](#)
[06](#)
[FMT1](#)
[00](#)
[MTB1](#)
[00](#)
[FMP1](#)
[00](#)
[FMB1](#)
[40](#)
[FMC8](#)
[00](#)
[FMM](#)
[800](#)
[FMM](#)
[80A](#)

25	BLE Temperature #1	2	Signed	-4000 12500 0.01*	°C	Degrees (°C), -40 - +125; Error codes: 4000 - abnormal sensor state 3000 - sensor not found 2000 - failed sensor data parsing	FMBX XX FMB0 01 FMC0 01 FMB0 10 FMB0 02 FMB0 20 FMB0 03 FMB1 10 FMB1 20 FMB1 22 FMB1 25 FMU1 25 FMC1 25 FMB1 30 FMU1 30 FMC1 30 FMB1 40 FMB1 50 FMC1 50 FMM 150 FMB9 00 FMB9 20 FMB9 10 FMB9 62 FMB9 64 FM30 01 FMB2 02 FMB2 04 FMB2 06 FMT1 00 MTB1 00 FMP1 00 FMB1 40 MSP5 00 FMC8 00 FMM 800 FMM 80A	Bluetooth Low Energy
----	--------------------	---	--------	-------------------	----	---	--	-------------------------

26	BLE Temperature #2	2	Signed	-4000 12500 0.01*	°C	Degrees (°C), -40 - +125; Error codes: 4000 - abnormal sensor state 3000 - sensor not found 2000 - failed sensor data parsing	FMBX XX FMB0 01 FMC0 01 FMB0 10 FMB0 02 FMB0 20 FMB0 03 FMB1 10 FMB1 20 FMB1 22 FMB1 25 FMU1 25 FMC1 25 FMB1 30 FMU1 30 FMC1 30 FMB1 40 FMB1 50 FMC1 50 FMM 150 FMB9 00 FMB9 20 FMB9 10 FMB9 62 FMB9 64 FM30 01 FMB2 02 FMB2 04 FMB2 06 FMT1 00 MTB1 00 FMP1 00 FMB1 40 MSP5 00 FMC8 00 FMM 800 FMM 80A	Bluetooth Low Energy
----	--------------------	---	--------	-------------------	----	---	--	-------------------------

27	BLE Temperature #3	2	Signe d	-4000 12500 0.01*	°C	Degrees (°C), -40 - +125; Error codes: 4000 - abnormal sensor state 3000 - sensor not found 2000 - failed sensor data parsing	FMBX XX FMB0 01 FMC0 01 FMB0 10 FMB0 02 FMB0 20 FMB0 03 FMB1 10 FMB1 20 FMB1 22 FMB1 25 FMU1 25 FMC1 25 FMB1 30 FMU1 30 FMC1 30 FMB1 40 FMB1 50 FMC1 50 FMM 150 FMB9 00 FMB9 20 FMB9 10 FMB9 62 FMB9 64 FM30 01 FMB2 02 FMB2 04 FMB2 06 FMT1 00 MTB1 00 FMP1 00 FMB1 40 MSP5 00 FMC8 00 FMM 800 FMM 80A	Bluetooth Low Energy
----	--------------------	---	------------	-------------------	----	---	--	-------------------------

28	BLE Temperature #4	2	Signed	-4000 12500 0.01*	°C	Degrees (°C), -40 - +125; Error codes: 4000 - abnormal sensor state 3000 - sensor not found 2000 - failed sensor data parsing	FMBX XX FMB0 01 FMC0 01 FMB0 10 FMB0 02 FMB0 20 FMB0 03 FMB1 10 FMB1 20 FMB1 22 FMB1 25 FMU1 25 FMC1 25 FMB1 30 FMU1 30 FMC1 30 FMB1 40 FMB1 50 FMC1 50 FMM 150 FMB9 00 FMB9 20 FMB9 10 FMB9 62 FMB9 64 FM30 01 FMB2 02 FMB2 04 FMB2 06 FMT1 00 MTB1 00 FMP1 00 FMB1 40 MSP5 00 FMC8 00 FMM 800 FMM 80A	Bluetooth Low Energy
----	--------------------	---	--------	-------------------	----	---	--	-------------------------

29	BLE Battery #1	1	Unsigned	0	100	-	%	Battery level of sensor #1	FMBX XX FMB0 01 FMC0 01 FMB0 10 FMB0 02 FMB0 20 FMB0 03 FMB1 10 FMB1 20 FMB1 22 FMB1 25 FMU1 25 FMC1 25 FMB1 30 FMU1 30 FMC1 30 FMB1 40 FMB1 50 FMC1 50 FMM 150 FMB9 00 FMB9 20 FMB9 10 FMB9 62 FMB9 64 FM30 01 FMB2 02 FMB2 04 FMB2 06 FMT1 00 MTB1 00 FMP1 00 FMB1 40 MSP5 00 FMC8 00 FMM 800 FMM 80A	Bluetooth Low Energy
----	----------------	---	----------	---	-----	---	---	----------------------------	--	-------------------------

20	BLE Battery #2	1	Unsigned	0	100	-	%	Battery level of sensor #2	FMBX XX FMB0 01 FMC0 01 FMB0 10 FMB0 02 FMB0 20 FMB0 03 FMB1 10 FMB1 20 FMB1 22 FMB1 25 FMU1 25 FMC1 25 FMB1 30 FMU1 30 FMC1 30 FMB1 40 FMB1 50 FMC1 50 FMM 150 FMB9 00 FMB9 20 FMB9 10 FMB9 62 FMB9 64 FM30 01 FMB2 02 FMB2 04 FMB2 06 FMT1 00 MTB1 00 FMP1 00 FMB1 40 MSP5 00 FMC8 00 FMM 800 FMM 80A	Bluetooth Low Energy
----	----------------	---	----------	---	-----	---	---	----------------------------	--	-------------------------

22	BLE Battery #3	1	Unsigned	0	100	-	%	Battery level of sensor #3	FMBX XX FMB0 01 FMC0 01 FMB0 10 FMB0 02 FMB0 20 FMB0 03 FMB1 10 FMB1 20 FMB1 22 FMB1 25 FMU1 25 FMC1 25 FMB1 30 FMU1 30 FMC1 30 FMB1 40 FMB1 50 FMC1 50 FMM 150 FMB9 00 FMB9 20 FMB9 10 FMB9 62 FMB9 64 FM30 01 FMB2 02 FMB2 04 FMB2 06 FMT1 00 MTB1 00 FMP1 00 FMB1 40 MSP5 00 FMC8 00 FMM 800 FMM 80A	Bluetooth Low Energy
----	----------------	---	----------	---	-----	---	---	----------------------------	--	-------------------------

23	BLE Battery #4	1	Unsigned	0	100	-	%	Battery level of sensor #4	FMBX XX FMB0 01 FMC0 01 FMB0 10 FMB0 02 FMB0 20 FMB0 03 FMB1 10 FMB1 20 FMB1 22 FMB1 25 FMU1 25 FMC1 25 FMB1 30 FMU1 30 FMC1 30 FMB1 40 FMB1 50 FMC1 50 FMM 150 FMB9 00 FMB9 20 FMB9 10 FMB9 62 FMB9 64 FM30 01 FMB2 02 FMB2 04 FMB2 06 FMT1 00 MTB1 00 FMP1 00 FMB1 40 MSP5 00 FMC8 00 FMM 800 FMM 80A	Bluetooth Low Energy
----	----------------	---	----------	---	-----	---	---	----------------------------	--	-------------------------

108	BLE Humidity #4	2	Unsigned	0	1000	0.1*	%RH	Humidity	FMBX XX FMB0 01 FMC0 01 FMB0 10 FMB0 02 FMB0 20 FMB0 03 FMB1 10 FMB1 20 FMB1 22 FMB1 25 FMU1 25 FMC1 25 FMB1 30 FMU1 30 FMC1 30 FMB1 40 FMB1 50 FMC1 50 FMM 150 FMB9 00 FMB9 20 FMB9 10 FMB9 62 FMB9 64 FM30 01 FMB2 02 FMB2 04 FMB2 06 FMT1 00 MTB1 00 FMP1 00 FMB1 40 MSP5 00 FMC8 00 FMM 800 FMM 80A	Bluetooth Low Energy
-----	-----------------	---	----------	---	------	------	-----	----------	--	-------------------------

270 BLE Fuel Level #1 2 Unsigned 0 65535 - - Fuel Level

FMBX
XX
[FMB0](#)
01
[FMC0](#)
01
[FMB0](#)
10
[FMB0](#)
02
[FMB0](#)
20
[FMB0](#)
03
[FMB1](#)
10
[FMB1](#)
20
[FMB1](#)
22
[FMB1](#)
25
[FMU1](#)
25
[FMC1](#)
25
[FMB1](#)
30
[FMU1](#)
30
[FMC1](#)
30
[FMB1](#)
40
[FMB1](#)
50
[FMC1](#) Bluetooth
50 Low Energy
[FMM](#)
150
[FMB9](#)
00
[FMB9](#)
20
[FMB9](#)
10
[FMB9](#)
62
[FMB9](#)
64
[FM30](#)
01
[FMB2](#)
02
[FMB2](#)
04
[FMB2](#)
06
[FMT1](#)
00
[MTB1](#)
00
[FMP1](#)
00
[FMB1](#)
40
[MSP5](#)
00
[FMC8](#)
00
[FMM](#)
800
[FMM](#)
80A

276	BLE Fuel Level #3	2	Unsigned	0	65535	-	-	Fuel Level	FMBX XX FMB0 01 FMC0 01 FMB0 10 FMB0 02 FMB0 20 FMB0 03 FMB1 10 FMB1 20 FMB1 22 FMB1 25 FMU1 25 FMC1 25 FMB1 30 FMU1 30 FMC1 30 FMB1 40 FMB1 50 FMC1 50 FMM 150 FMB9 00 FMB9 20 FMB9 10 FMB9 62 FMB9 64 FM30 01 FMB2 02 FMB2 04 FMB2 06 FMT1 00 MTB1 00 FMP1 00 FMB1 40 MSP5 00 FMC8 00 FMM 800 FMM 80A	Bluetooth Low Energy
-----	-------------------	---	----------	---	-------	---	---	------------	--	-------------------------

463	BLE 1 Custom #2	4	UNSI GNED LONG INT	0	21474 83647	-	-	Custom IO element for BLE sensor	FMBX XX FMB0 01 FMC0 01 FMB0 10 FMB0 02 FMB0 20 FMB0 03 FMB1 10 FMB1 20 FMB1 22 FMB1 25 FMU1 25 FMC1 25 FMB1 30 FMU1 30 FMC1 30 FMB1 40 FMB1 50 FMC1 50 FMM 150 FMB9 00 FMB9 20 FMB9 10 FMB9 62 FMB9 64 FM30 01 FMB2 02 FMB2 04 FMB2 06 FMT1 00 MTB1 00 FMP1 00 FMB1 40 MSP5 00 FMC8 00 FMM 800 FMM 80A	Bluetooth Low Energy
-----	-----------------	---	-----------------------------	---	----------------	---	---	----------------------------------	--	-------------------------

464	BLE 1 Custom #3	8	UNSI GNED LONG INT	0	42949 67295	-	-	Custom IO element for BLE sensor	FMBX XX FMB0 01 FMC0 01 FMB0 10 FMB0 02 FMB0 20 FMB0 03 FMB1 10 FMB1 20 FMB1 22 FMB1 25 FMU1 25 FMC1 25 FMB1 30 FMU1 30 FMC1 30 FMB1 40 FMB1 50 FMC1 50 FMM 150 FMB9 00 FMB9 20 FMB9 10 FMB9 62 FMB9 64 FM30 01 FMB2 02 FMB2 04 FMB2 06 FMT1 00 MTB1 00 FMP1 00 FMB1 40 MSP5 00 FMC8 00 FMM 800 FMM 80A	Bluetooth Low Energy
-----	-----------------	---	-----------------------------	---	----------------	---	---	----------------------------------	--	-------------------------

465	BLE 1 Custom #4	8	UNSI GNED LONG INT	0	42949 67295	-	-	Custom IO element for BLE sensor	FMBX XX FMB0 01 FMC0 01 FMB0 10 FMB0 02 FMB0 20 FMB0 03 FMB1 10 FMB1 20 FMB1 22 FMB1 25 FMU1 25 FMC1 25 FMB1 30 FMU1 30 FMC1 30 FMB1 40 FMB1 50 FMC1 50 FMM 150 FMB9 00 FMB9 20 FMB9 10 FMB9 62 FMB9 64 FM30 01 FMB2 02 FMB2 04 FMB2 06 FMT1 00 MTB1 00 FMP1 00 FMB1 40 MSP5 00 FMC8 00 FMM 800 FMM 80A	Bluetooth Low Energy
-----	-----------------	---	-----------------------------	---	----------------	---	---	----------------------------------	--	-------------------------

467	BLE 2 Custom #2	8	UNSI GNED LONG INT	0	42949 67295	-	-	Custom IO element for BLE sensor	FMBX XX FMB0 01 FMC0 01 FMB0 10 FMB0 02 FMB0 20 FMB0 03 FMB1 10 FMB1 20 FMB1 22 FMB1 25 FMU1 25 FMC1 25 FMB1 30 FMU1 30 FMC1 30 FMB1 40 FMB1 50 FMC1 50 FMM 150 FMB9 00 FMB9 20 FMB9 10 FMB9 62 FMB9 64 FM30 01 FMB2 02 FMB2 04 FMB2 06 FMT1 00 MTB1 00 FMP1 00 FMB1 40 MSP5 00 FMC8 00 FMM 800 FMM 80A	Bluetooth Low Energy
-----	-----------------	---	-----------------------------	---	----------------	---	---	----------------------------------	--	-------------------------

469	BLE 2 Custom #4	8	UNSI GNED LONG INT	0	42949 67295	-	-	Custom IO element for BLE sensor	FMBX XX FMB0 01 FMC0 01 FMB0 10 FMB0 02 FMB0 20 FMB0 03 FMB1 10 FMB1 20 FMB1 22 FMB1 25 FMU1 25 FMC1 25 FMB1 30 FMU1 30 FMC1 30 FMB1 40 FMB1 50 FMC1 50 FMM 150 FMB9 00 FMB9 20 FMB9 10 FMB9 62 FMB9 64 FM30 01 FMB2 02 FMB2 04 FMB2 06 FMT1 00 MTB1 00 FMP1 00 FMB1 40 MSP5 00 FMC8 00 FMM 800 FMM 80A	Bluetooth Low Energy
-----	-----------------	---	-----------------------------	---	----------------	---	---	----------------------------------	--	-------------------------

470	BLE 2 Custom #5	8	UNSI GNED LONG INT	0	42949 67295	-	-	Custom IO element for BLE sensor	FMBX XX FMB0 01 FMC0 01 FMB0 10 FMB0 02 FMB0 20 FMB0 03 FMB1 10 FMB1 20 FMB1 22 FMB1 25 FMU1 25 FMC1 25 FMB1 30 FMU1 30 FMC1 30 FMB1 40 FMB1 50 FMC1 50 FMM 150 FMB9 00 FMB9 20 FMB9 10 FMB9 62 FMB9 64 FM30 01 FMB2 02 FMB2 04 FMB2 06 FMT1 00 MTB1 00 FMP1 00 FMB1 40 MSP5 00 FMC8 00 FMM 800 FMM 80A	Bluetooth Low Energy
-----	-----------------	---	-----------------------------	---	----------------	---	---	----------------------------------	--	-------------------------

473	BLE 3 Custom #4	8	UNSI GNED LONG INT	0	42949 67295	-	-	Custom IO element for BLE sensor	FMBX XX FMB0 01 FMC0 01 FMB0 10 FMB0 02 FMB0 20 FMB0 03 FMB1 10 FMB1 20 FMB1 22 FMB1 25 FMU1 25 FMC1 25 FMB1 30 FMU1 30 FMC1 30 FMB1 40 FMB1 50 FMC1 50 FMM 150 FMB9 00 FMB9 20 FMB9 10 FMB9 62 FMB9 64 FM30 01 FMB2 02 FMB2 04 FMB2 06 FMT1 00 MTB1 00 FMP1 00 FMB1 40 MSP5 00 FMC8 00 FMM 800 FMM 80A	Bluetooth Low Energy
-----	-----------------	---	-----------------------------	---	----------------	---	---	----------------------------------	--	-------------------------

476	BLE 4 Custom #3	8	UNSI GNED LONG INT	0	42949 67295	-	-	Custom IO element for BLE sensor	FMBX XX FMB0 01 FMC0 01 FMB0 10 FMB0 02 FMB0 20 FMB0 03 FMB1 10 FMB1 20 FMB1 22 FMB1 25 FMU1 25 FMC1 25 FMB1 30 FMU1 30 FMC1 30 FMB1 40 FMB1 50 FMC1 50 FMM 150 FMB9 00 FMB9 20 FMB9 10 FMB9 62 FMB9 64 FM30 01 FMB2 02 FMB2 04 FMB2 06 FMT1 00 MTB1 00 FMP1 00 FMB1 40 MSP5 00 FMC8 00 FMM 800 FMM 80A	Bluetooth Low Energy
-----	-----------------	---	-----------------------------	---	----------------	---	---	----------------------------------	--	-------------------------

