

Template:SAS device Parameter list - Data Acquisition

□

Contents

- [1 Data Acquisition](#)
 - [1.1 On Stop](#)
 - [1.2 Moving](#)
 - [1.3 On Demand tracking](#)
 - [1.4 Race Mode](#)

Data Acquisition

On Stop

Parameter ID	Parameter Type	Default value	Value range		Value	Parameter name	Network GSM operator
			Min	Max			
10000	Uint16	3600	0	65535	Seconds	Min Period	Home
10004	Uint8	1	1	255	Value	Min Saved Records	
10005	Uint16	120	0	65535	Seconds	Send Period	
10100	Uint16	3600	0	65535	Seconds	Min Period	Roaming
10104	Uint8	1	1	255	Value	Min Saved Records	
10105	Uint16	0	0	65535	Seconds	Send Period	Unknown
10200	Uint16	3600	0	65535	Seconds	Min Period	
10204	Uint8	1	1	255	Value	Min Saved Records	
10205	Uint16	120	0	65535	Seconds	Send Period	

Moving

Parameter ID	Parameter Type	Default value	Value range		Value	Parameter name	Network GSM operator
			Min	Max			
10050	Uint16	300	0	65535	Seconds	Min Period	Home
10051	Uint16	100	0	65535	Meters	Min Distance	
10052	Uint8	10	0	180	Degrees	Min Angle	
10053	Uint8	10	0	100	Value	Min Speed Delta	Roaming
10054	Uint8	1	1	255	Value	Min Saved Records	
10055	Uint16	120	0	65535	Seconds	Send Period	
10150	Uint16	300	0	65535	Seconds	Min Period	
10151	Uint16	100	0	65535	Meters	Min Distance	
10152	Uint8	10	0	180	Degrees	Min Angle	Unknown
10153	Uint8	10	0	100	Value	Min Speed Delta	
10154	Uint8	1	1	255	Value	Min Saved Records	
10155	Uint16	120	0	65535	Seconds	Send Period	
10250	Uint16	300	0	65535	Seconds	Min Period	
10251	Uint16	100	0	65535	Meters	Min Distance	Unknown
10252	Uint8	10	0	180	Degrees	Min Angle	
10253	Uint8	10	0	100	Value	Min Speed Delta	
10254	Uint8	1	1	255	Value	Min Saved Records	
10255	Uint16	120	0	65535	Seconds	Send Period	

On Demand tracking

Parameter ID	Parameter Type	Default value	Value range		Value	Parameter name
			Min	Max		
10990	Uint8	10	5	60	Seconds	Tracking period
10991	Uint16	600	300	3600	Seconds	Tracking duration

Race Mode

Parameter ID	Parameter Type	Default value	Value range		Value	Parameter name
			Min	Max		
10993	Uint8	0	0	1	0 - Disable 1 - Enable	Race Mode