

FMA getinfo

Example:

"INI:2013/10/11 8:44 RTC:2013/10/11 8:59 RST:1 ERR:0 SR:0 BR:0 CF:0 FG:0 FL:0 UT:0 [SMS:1](#)
NOGPS:0:14 GPS:2 SAT:0 RS:3 MD:4 RF:0"

Response details	Description
INIT	Device initialization time.
RTC	RTC time.
RST	Total restarts count.
ERR	Error Counter.
SR	Number of Sent Records.
BR	Number of broken Records.
CF	Profile CRC Fail counter
FG	Failed GPRS counter.
FL	Failed link counter.
UT	UPD Timeout counter.
SMS	Sent SMS counter.
NOGPS	No GPS Timer.
GPS	GPS receiver state. 0 - OFF, 1 - restarting, 2 - ON but no fix, 3 - ON and operational, 4 - sleep mode.
SAT	Average satellites.
RS	Reset Source Identification 1 - Low Power, 2 - W Watchdog, 3 - I Watchdog, 4 - Software reset, 5 - Power On, 6 - Pin Reset.
MD	Data Mode state. 0 - Home and Stop, 1 - Home and Moving, 2 - Roaming and Stop, 3 - Roaming and Moving, 4 - Unknown and Stop, 5 - Unknown and Moving.
RF	Records Found - number of records in the memory.