

FMM00A Bluetooth® settings

[Main Page](#) > [OBd Trackers](#) > [FMM00A](#) > [FMM00A Configuration](#) > **FMM00A Bluetooth® settings**



Contents

- [1 Disclaimer](#)
- [2 General functionality](#)
- [3 Auto Connect to External Device](#)
 - [3.1 Bluetooth solutions](#)

Disclaimer



If you are not using Bluetooth, **please consider turning it off** or **change Bluetooth PIN** to remove potential risks.

If you are using Bluetooth we strongly recommend **using AES encryption** for enhanced security.

General functionality

General

BT Radio

| | |
|-------------------------|-----------------|
| Disable | Enable (hidden) |
| Enable (visible) | |

Local Name

Local PIN

Security Mode

| | |
|-----------------|----------------|
| PIN only | PIN + MAC list |
| MAC list only | None |

General functionality configures Bluetooth to work in slave mode. This mode allows any external device to connect to FMM00A.

Parameter *BT Radio* allows enabling or disabling Bluetooth. There are three different settings:

- **Disabled** - Bluetooth functionality will be disabled.
- **Enable (hidden)** - Bluetooth functionality will be enabled, external devices will be able to connect to FMM00A, but no devices will be able to detect it.
- **Enable (visible)** - Bluetooth functionality will be enabled and any external device will be able to detect and connect to FMM00A.

It is possible to configure the Local name of the device, as well as the Local PIN, which will be used when trying to pair with the FMM00A device. There are two different parameters:

- **Local Name** parameter lets user declare a visible name of FMM00A to external devices.
- **Local PIN** parameter lets user configure Bluetooth PIN of FMM00A device.

The FMM00A supports composed Bluetooth Local names, which allows the user to have a predefined number of IMEI digits at the end of the device name. The format of the composed Bluetooth name looks like this:

Device name + %imeiX

X - how many digits will be taken from IMEI to show in Local name, digits will be taken from the end of IMEI. Minimum value of X is 1 and the Maximum value is 15.


Example:

If the configured Local Name parameter is "FMB_120_%imei7" and the IMEI of the device is 352093089520901, name will be displayed as **FMB_120_9520901** (whether "_LE" is added at the end depends on whether device supports BLE or not. The full name of the device, which supports BLE would be **FMB_120_9520901_LE**).

If the Local Name is written incorrectly, the Bluetooth name of the device will be broadcasted as it is. An example can be seen below.

Example:

If the configured Local Name parameter is "FMB_120_%ime7" devices name will be broadcasted as **FMB_120_%ime7** or if wrong X will be configured, for example "FMB_120_%imei20" devices name will broadcasted as **FMB_120_%imei20**.

 The Composed Bluetooth name is supported from 03.25.05 firmware version.

FMM00A Bluetooth has several different *Security Modes*:

- **PIN only** - only Local PIN will be reacquired to complete connection to FMM00A.
- **PIN + MAC list** - PIN and Authorized Devices MAC List will be checked against to allow connection to FMM00A. If the external device MAC ID is in the list and correct *Local PIN* is entered then connection will be established, otherwise FMM00A will reject connection.
- **MAC list only** - only *Authorized Devices MAC List* will be checked when trying to connect to FMM00A. If external device MAC ID is in the list then connection will be established, otherwise FMM00A will reject connection.
- **None** - neither *Local PIN* nor *Authorized Device MAC List* will be checked.

Auto Connect to External Device



Auto connection functionality configures FMM00A as master device, which allows connecting FMM00A to an external device. FMM00A currently supports these modes:

- **None** - disables auto connection functionality.

- **Data Link** - BT Data link mode is enabled by Configurator *Data Link* parameter: when **Data Link** is configured and FMB has a link with the server, paired device can send messages via Bluetooth SPP profile directly to the server. Messages will be encoded by [Codec12](#).
- **Inateck Scanner** - FMM00A automatically connects to Inateck BT Barcode Scanner BCST-70 and will be ready to receive data (coded in barcode). *Scanner must be configured for using "ENTER" as suffix*. FMM00A supports online and inventory mode. A new record will be generated on every data portion received from scanner via SPP. Data will be stored with AVL ID 264, variable data length, max length is 32 bytes. *Note: Added from FW version 03.16.00.Rev.00+*
- **User ID** - This mode makes FMM00A connect automatically to a device and stores its BT MAC address in I/O element *User ID* (I/O ID: 50520). This is used for driver authentication. If there's no connection, the I/O element value is set to 0.

FMM00A supports ONE connection at a time.

- ✘ FMM00A can see up to 10 available devices. If there are more than 10 devices, the list may change with each new scan.

Bluetooth solutions

- [Logging the FMM00A device using your mobile phone](#)