Getting Started

Here you will discover basic information on what FM devices support FOTA Web solution and where you can get started by following step by step guide from the invitation to your first login. Additionally you will find web sites basic settings such as changing language, API and more.

Contents

- <u>1 Device requirements</u>
- 2 Network requirements
- <u>3 How to access FOTA WEB</u>
- <u>4 Select company</u>
- <u>5 Notifications</u>

Device requirements

Supported Devices

×	×	×
Basic Trackers Rich tracking	Fast & Easy Trackers	Advanced Trackers
features at a competitive price	Fast installation and accurate tracking	Flexible and sophisticated all rounders
Product list	Product list	Product list [+/
[+/-] FMB900 FMB910 FMB920 FMC920 FMM920 FMB930 IP67 Trackers FMB965 Fleet Telematics Trackers FTC921 FTC921 FTC961	[+/-] FMP100 FMB010 FMB020 FMC800 FMM800 FMM80A IP65 Trackers FMT100 FMC880 FMM880 Fleet Telematics Trackers FTC881] FMB110 FMB120 FMB122 FMB130 FMC130 FMC13A FMC13A FMM130 FMM13A IP67 Trackers FMB202 FMB204 FMB209 FMB230
		FMC230

FMC234 FMM230

×	×	×
OBD	CAN Trackers	Professional
Trackers	Provide CAN bus data for	Trackers
Compact	all vehicle types	Comprehensive
Plug & Play models to	Product list [+/-] FMB140 FMB150	solutions for professional use
read OBD II data	<u>FMC150</u> FMM150	Product list [+/-]
Product	LV-CAN200	FMB641
list [+/-]	<u>ALL-CAN300</u>	<u>FMC650</u>
<u>FMB001</u>	<u>CAN-CONTROL</u>	<u>FMM650</u>
<u>FMB002</u>	ECAN02	<u>FMB125</u>
<u>FMB003</u>	IP67 Trackers	<u>FMC125</u>
<u>FMC001</u>	<u>FMB240</u>	<u>FMM125</u>
<u>FMC003</u>		IP67 Trackers
<u>FMC00A</u>		<u>FMB225</u>
<u>FMM001</u>		<u>FMC225</u>
FMM003		
<u>FMM00A</u>		

Note: 1. All FMBXXX devices except for FMB64X should have at least 01.03.03.Rev.00 firmware version installed.

2. FMB64X should have at least 00.02.05 version installed.

3. FM36YX devices should have at least $\underline{01.12.00.\text{Rev.}02}$ version installed. (FM36YX FotaWeb functionality for firmware update only)

Please check <u>Firmware Link</u> to find latest base firmware for your device.

Default FOTA WEB configuration settings:

Domain: fota.teltonika.lt **Port:** 5000 **Period:** 720 minutes (every 720 minutes device shall connect to FOTA WEB)

×

Network requirements

If your SIM cards are within Mobile Operator's VPN (private APN), the following must be ensured and paid special attention.

1. Must ensure that domain <u>https://fota.teltonika.lt</u> can be resolved from within Operator's network.

 $\mathbf{2.}$ Following IP and ports (egress) must be allowed by the operator.

- IP: 35.156.7.140
- Ports:
 - · 2000
 - 3000
 - $\circ \ 4000$
 - · 5000

· 6000 · 7000

When using VPN SIM cards, you should still configure https://fota.teltonika.lt domain in your configurator, not the plain IP address.

How to access FOTA WEB

FOTA WEB is reached using domain address https://fota.teltonika.lt. FOTA WEB uses HTTP ports 80 and 85 for authentication so if your network has HTTP proxy service or is blocking outgoing traffic - make sure that those two ports are added to exceptions in network proxy service and firewall.

1. Invitation for FOTA WEB is being delivered to user e-mail. Press the URL to create a password for your account.

you will be asked to create a password for your account.

×

3. Last step is logging into FOTA WEB with the newly created 2. After pressing the URL Link account by entering your email address and password for your account. Email address is the same as the address you've received the invitation.

×

×

Select company

At the top-right corner, you can find the **Company selector** button. Pressing on a button will open a list of parent and child companies. Selecting a company allows for filtering resources available such as devices, task groups, groups, users, and files. It is an easy way to separate resources and make sure that you are working with the correct ones. Company selector button behavior:

- When a single company is selected, you will see the company button label change to the selected company's name.
- When two or more companies are selected, you will see a number of companies selected instead of an icon and "Companies" label.
- When nothing is selected, you will see everything available and "All companies" label.

Note: Every company has to be selected individually.



Notifications

Notifications is located at the top-right corner of the page. Notifications will inform you when certain actions are completed such as devices firmware got updated, configuration got uploaded to or downloaded from the device and also notifies when devices are transferred from one company to another or moved from main company to child company.

	പ്പെ All companie	s ² Notifications	绞 Settings
Notifications			×
New	ı	Seen	
2023-06-05 15:04:31 Resource update 0 companies proce	succeeded		×
2023-06-05 15:04:25 Resource update 2 companies proce	ssed		×
<u>Mark all as seen</u>			