

TAT240 SMS/GPRS Commands

[Main Page](#) > [Autonomous Trackers](#) > [TAT240](#) > [TAT240 Manual](#) > **TAT240 SMS/GPRS Commands**

All commands are case sensitive. When a user tries to send an SMS/GPRS message to TAT240, most of the time it cannot arrive because the GSM/GPRS module is disabled between sending of records. The device will receive the SMS/GPRS message when it wakes up to send a record according to the configured tracking period or scheduled time. In order to quickly execute the SMS/GPRS command and receive a response, the user should send the message immediately after receiving a tracking record.

SMS command structure:

<SMS login><space><SMS password><space><command><space><value>

SMS command [getinfo](#) example:

- If you have set SMS login and password: login pass getinfo
- If SMS login and password are not set leave two spaces before command: getinfo

GPRS commands require [Codec 12](#) protocol.

□

Contents

- [1 Common commands](#)

To search for compatible products, [Expand all content](#)

Common commands

Command	Description	Response	HW Support	Parameter Group
getinfo	Device runtime system information.	Yes	[Expand] TAT100 TAT140 TAT141 TAT240	Common commands
getver	Returns code version, device IMEI, modem app version, RTC time, Init time, Uptime and BT MAC address.	Yes	[Expand] TAT100 TAT140 TAT141 TAT240	Common commands
getstatus	Modem Status information.	Yes	[Expand] TAT100 TAT140 TAT141 TAT240	Common commands
getgps	Current GPS data, date and time.	Yes	[Expand] TAT100 TAT140 TAT141 TAT240	Common commands
cpureset	resets device device modem	No	[Expand] TAT100 TAT140 TAT141 TAT240	Common commands
fwstats	Get data about FW and restarts	Yes	[Expand] TAT100 TAT140 TAT141 TAT240	Common commands
getrecord	SMS command initiates saving and sending of high priority record	No	[Expand] TAT100 TAT140 TAT141 TAT240	Common commands

<i>gettimeiccid #</i>	Response is sent to SMS/GPRS command sender and also to GSM number provided. 1.# GSM number using international format e.g. 37069012345	Yes	[Expand] TAT100 TAT140 TAT141 TAT240	Common commands
<i>getimsi</i>	Sends the IMSI number of the SIM card inserted as a response to the sender.	Yes	[Expand] TAT100 TAT140 TAT141 TAT240	Common commands
<i>allver</i>	Responds with information about hardware and modem firmware version and storage space	Yes	[Expand] TAT100 TAT140 TAT141 TAT240	Common commands
<i>getparam #</i>	Returns selected parameter value. 1.# - first ID value . 2.# - second ID value . 3.# - third ID value . SMS command is limited to 160 characters.	Yes	[Expand] TAT100 TAT140 TAT141 TAT240	Common commands
<i>getparam #;#;...</i>	Sets selected parameter value			
<i>setparam #:#</i>	[Parameter ID] : [New Parameter Value] ; [Parameter ID] : [New Parameter Value]...	Yes	[Expand] TAT100 TAT140 TAT141 TAT240	Common commands
<i>setparam #:#;#;#;#;...</i>	SMS command is limited to 160 characters.			
<i>flush #,#,#,#,#,#,#</i>	Redirects device to other server. 1.# - IMEI. 2.# - APN. 3.# - LOGIN. 4.# - PASS. 5.# - IP. 6.# - PORT. 7.# - MODE (0-TCP/1-UDP).	Yes	[Expand] TAT100 TAT140 TAT141 TAT240	Common commands
<i>countrecs</i>	Returns records number.	Yes	[Expand] TAT100 TAT140 TAT141 TAT240	Common commands
<i>web_connect</i>	Connect to Fota WEB after receives the command. TAT100 receives GPRS/SMS commands after it wakes up.	Yes	[Expand] TAT100 TAT140 TAT141 TAT240	Common commands
<i>deleterecords</i>	Delete all records from SD card.	Yes	[Expand] TAT100 TAT140 TAT141 TAT240	Common commands
<i>wdlog</i>	Returns all information about 'watch dogs'	Yes	[Expand] TAT100 TAT140 TAT141 TAT240	Common commands
<i>defaultcfg</i>	Load default configuration.	Yes	[Expand] TAT100 TAT140 TAT141 TAT240	Common commands
<i>setkey # #</i>	Add new or change current configuration keyword. If device is locked, keyword cannot be changed. 1.# - old keyword (if adding new keyword space). 2.# - new keyword.	Yes	[Expand] TAT100 TAT140 TAT141 TAT240	Common commands
<i>delkey #</i>	Remove existing keyword (If device is locked, keyword cannot be changed). 1.# - old keyword.	Yes	[Expand] TAT100 TAT140 TAT141 TAT240	Common commands
<i>bbread #</i>	Return black box information (HEX value of event ID and HEX value of custom data field (optional)). 1.# - returns entered number of latest events. When # is omitted the latest events are packed to single SMS.	Yes	[Expand] TAT100 TAT140 TAT141 TAT240	Common commands
<i>bbinfo #</i>	Return same information as bbread command but additional all events timestamp is written in HEX. 1.# - returns entered number of latest events. When # is omitted the latest events are packed to single SMS.	Yes	[Expand] TAT100 TAT140 TAT141 TAT240	Common commands
<i>sdformat</i>	Format SD card.	Yes	[Expand] TAT100 TAT140 TAT141 TAT240	Common commands