

Template:FMX640 BLE ID

BLE

Property ID in AVL packet	Property Name	Bytes	Type	Value range		Multiplier	Units	Description	FW Support	Parameter Group
				Min	Max					
701	BLE Temperature 1	2	Signed	0	0xFFFF	-	-		FMX640 FMX640	BLE elements
702	BLE Temperature 2	2	Signed	0	0xFFFF	-	-		FMX640 FMX640	BLE elements
703	BLE Temperature 3	2	Signed	0	0xFFFF	-	-		FMX640 FMX640	BLE elements
704	BLE Temperature 4	2	Signed	0	0xFFFF	-	-		FMX640 FMX640	BLE elements
705	BLE Battery 1	1	Unsigned	0	0xFF	-	-		FMX640 FMX640	BLE elements
706	BLE Battery 2	1	Unsigned	0	0xFF	-	-		FMX640 FMX640	BLE elements
707	BLE Battery 3	1	Unsigned	0	0xFF	-	-		FMX640 FMX640	BLE elements
708	BLE Battery 4	1	Unsigned	0	0xFF	-	-		FMX640 FMX640	BLE elements
709	BLE Humidity 1	2	Unsigned	0	0xFFFF	-	-		FMX640 FMX640	BLE elements
710	BLE Humidity 2	2	Unsigned	0	0xFFFF	-	-		FMX640 FMX640	BLE elements
711	BLE Humidity 3	2	Unsigned	0	0xFFFF	-	-		FMX640 FMX640	BLE elements
712	BLE Humidity 4	2	Unsigned	0	0xFFFF	-	-		FMX640 FMX640	BLE elements
713	BLE Sensor Custom 1	8	Unsigned	0	0xFFFFFFFFFFFFFF	-	-		FMX640 FMX640	BLE elements
714	BLE Sensor Custom 2	8	Unsigned	0	0xFFFFFFFFFFFFFF	-	-		FMX640 FMX640	BLE elements
715	BLE Sensor Custom 3	8	Unsigned	0	0xFFFFFFFFFFFFFF	-	-		FMX640 FMX640	BLE elements
716	BLE Sensor Custom 4	8	Unsigned	0	0xFFFFFFFFFFFFFF	-	-		FMX640 FMX640	BLE elements
717	BLE Hum 1	2	Unsigned	0	0xFFFF	-	-		FMX640 FMX640	BLE elements
718	BLE Hum 2	2	Unsigned	0	0xFFFF	-	-		FMX640 FMX640	BLE elements
719	BLE Hum 3	2	Unsigned	0	0xFFFF	-	-		FMX640 FMX640	BLE elements
720	BLE Hum 4	2	Unsigned	0	0xFFFF	-	-		FMX640 FMX640	BLE elements
721	BLE LLS Fuel 1	2	Unsigned	0	0xFFFF	-	-		FMX640 FMX640	BLE elements
722	BLE LLS Fuel 2	2	Unsigned	0	0xFFFF	-	-		FMX640 FMX640	BLE elements
723	BLE LLS Fuel 3	2	Unsigned	0	0xFFFF	-	-		FMX640 FMX640	BLE elements
724	BLE LLS Fuel 4	2	Unsigned	0	0xFFFF	-	-		FMX640 FMX640	BLE elements
725	BLE Freq 1	4	Unsigned	0	0xFFFFFFFF	-	-		FMX640 FMX640	BLE elements
726	BLE Freq 2	4	Unsigned	0	0xFFFFFFFF	-	-		FMX640 FMX640	BLE elements
727	BLE Freq 3	4	Unsigned	0	0xFFFFFFFF	-	-		FMX640 FMX640	BLE elements
728	BLE Freq 4	4	Unsigned	0	0xFFFFFFFF	-	-		FMX640 FMX640	BLE elements
729	BLE Sensor Custom 12	4	Unsigned	0	0xFFFFFFFF	-	-		FMX640 FMX640	BLE elements
730	BLE Sensor Custom 13	4	Unsigned	0	0xFFFFFFFF	-	-		FMX640 FMX640	BLE elements
731	BLE Sensor Custom 14	4	Unsigned	0	0xFFFFFFFF	-	-		FMX640 FMX640	BLE elements
732	BLE Sensor Custom 15	4	Unsigned	0	0xFFFFFFFF	-	-		FMX640 FMX640	BLE elements
733	BLE Sensor Custom 22	4	Unsigned	0	0xFFFFFFFF	-	-		FMX640 FMX640	BLE elements
734	BLE Sensor Custom 23	4	Unsigned	0	0xFFFFFFFF	-	-		FMX640 FMX640	BLE elements
735	BLE Sensor Custom 24	4	Unsigned	0	0xFFFFFFFF	-	-		FMX640 FMX640	BLE elements
736	BLE Sensor Custom 25	4	Unsigned	0	0xFFFFFFFF	-	-		FMX640 FMX640	BLE elements
737	BLE Sensor Custom 32	4	Unsigned	0	0xFFFFFFFF	-	-		FMX640 FMX640	BLE elements
738	BLE Sensor Custom 33	4	Unsigned	0	0xFFFFFFFF	-	-		FMX640 FMX640	BLE elements
739	BLE Sensor Custom 34	4	Unsigned	0	0xFFFFFFFF	-	-		FMX640 FMX640	BLE elements
740	BLE Sensor Custom 35	4	Unsigned	0	0xFFFFFFFF	-	-		FMX640 FMX640	BLE elements
741	BLE Sensor Custom 42	4	Unsigned	0	0xFFFFFFFF	-	-		FMX640 FMX640	BLE elements
742	BLE Sensor Custom 43	4	Unsigned	0	0xFFFFFFFF	-	-		FMX640 FMX640	BLE elements
743	BLE Sensor Custom 44	4	Unsigned	0	0xFFFFFFFF	-	-		FMX640 FMX640	BLE elements
744	BLE Sensor Custom 45	4	Unsigned	0	0xFFFFFFFF	-	-		FMX640 FMX640	BLE elements
10500	BLE Advertisement data	Variable	HEX	0	1024	-	-	List of parsed advertising data of BLE beacons (Edbytsone and (Beacons) found by BLE scanning	FMX640 FMX640	BLE elements
548	Advanced BLE Advertisement data	Variable	HEX	0	1024	-	-	List of parsed <u>subsetting data of BLE beacons</u> (Edbytsone and (Beacons) found by BLE scanning	FMX640 FMX640	BLE elements