

FM36 getinfo

Response details	Description
INI	Device Initialization Time
RTC	RTC Time
RST	Restart Counter
ERR	Error Counter
SR	Number of Sent Records
BR	Number of broken records
CF	Profile CRC Fail counter
FG	Failed GPRS counter
FL	Failed link counter
UT	UPD Timeout counter
SMS	Sent SMS Counter
NOGPS	No GPS Timer
GPS	GPS receiver state. 0 - OFF, 1 - restarting, 2 - ON but no fix, 3 - ON and operational, 4 - sleep mode
SAT	Average satellites

RS Reset Source Identification
1 - Low Power,
2 - Watchdog,
3 - I Watchdog,
4 - Software reset,
5 - Power On,
6 - Pin Reset

MD Data Mode state. 0 - Home and Stop,
1 - Home and Moving,
2 - Roaming and Stop,
3 - Roaming and Moving,
4 - Unknown and Stop,
5 - Unknown and Moving

RF Records Found - number of records in the memory.

Example: INI:2013/10/11 8:44 RTC:2013/10/11 8:59 RST:1 ERR:0 SR:0 BR:0 CF:0 FG:0 FL:0 UT:0
[SMS:1](#) NOGPS:0:14 GPS:2 SAT:0 RS:3 MD:4 RF:0