

# Template:FMB Device Family Beacon List Parameter list

## Beacon List Parameters

Parameter ID	Parameter Type	Default value	Value Range		Value	Parameter Name
			Min	Max		
134	UInt8	0	0	2	0 - Disabled 1 - All 2 - Configured	Beacon Detection
136	UInt8	0	0	1	0 - Eventual 1 - Periodic	Beacon Record
137	UInt32	60	0	259200	Seconds	Record Period on Move (s)
139	UInt32	60	0	259200	Seconds	Record Period on Stop (s)

Beacon List

Parameter ID	iBeacon	EddyStone
1600		
...	UUID: Major: Minor	Namespace: Instance ID
1624		

Example:

```
<login><space><password><space>setparam  
1600:4B5C049F515341FCA950D2C264414E10-0005-0006  
<login><space><password><space>setparam 1600:00112233445566778899-ABCDE0810047
```