

Command: getinfo



Example:

```
RTC:2017/6/16 7:13 Init:2017/6/16 5:44 UpTime:4744s PWR:PwrVoltage RST:0  
GPS:2 SAT:0 TTFF:0 TTLF:0 NOGPS: 1:18 SR:0 FG:200 FL:0 SMS: 3 REC:42 MD:1  
DB:0
```

Response details	Description	Example
RTC	RTC time.	RTC:2017/6/16 7:13
Init	Device initialization time.	Init:2017/6/16 5:44
UpTime	Total up time (in seconds).	UpTime:4744s
PWR	Last restart reason.	PWR:PwrVoltage
RST	Total abnormal restarts count.	RST:0
GPS	GPS receiver state. 0 - OFF 1 - ON without fix 2 - ON with fix 3 - Sleep mode	GPS:2
SAT	Satellites in use.	SAT:0
TTFF	Time To First Fix.	TTFF:0
TTLF	Time To Last Fix.	TTLF:0
NOGPS	How much time no GPS fix (h:min).	NOGPS: 1:18
SR	Number of Sent Records.	SR:0
FG	Failed GPRS counter.	FG:200

FL	Failed link counter.	FL:0
SMS	Sent SMS counter.	SMS :3
REC	Records Found - number of records in the memory.	REC:42
MD	Data Mode state. 0 - Home and Stop 1 - Home and Moving 2 - Roaming and Stop 3 - Roaming and Moving 4 - Unknown and Stop 5 - Unknown and Moving	MD:1
DB	DB Values: 0 - SD Card used for records 1 - RAM Drive used for records	DB:0