

# FMB getver



Example:

```
Ver:02.00.01_06 GPS:AXN_3.80_3333_16070400,0000,, Hw:TFT100 Mod:1  
IMEI:352094000000000 Init: 2017-6-16 5:54 Uptime: 16574 MAC:002E43912EF7  
SPC:0(0) AXL:0 OBD:0 BL:1.6 BT:4
```

| Response details | Description                   | Example                           |
|------------------|-------------------------------|-----------------------------------|
| <b>Ver</b>       | Firmware version              | Ver:02.00.01_06                   |
| <b>GPS</b>       | Version of GPS module         | GPS:AXN_3.80_3333_16070400,0000,, |
| <b>Hw</b>        | Version of hardware           | Hw:TFT100                         |
| <b>Mod</b>       | Hardware version modification | Mod:1                             |
| <b>IMEI</b>      | Device IMEI                   | IMEI:352094000000000              |
| <b>Init</b>      | Command initialization time   | Init: 2017-6-16 5:54              |
| <b>Uptime</b>    | Total up time (in seconds)    | Uptime: 16574                     |
| <b>MAC</b>       | Bluetooth® MAC address        | MAC:002E43912EF7                  |
| <b>SPC</b>       | Spec ID                       | SPC:0(0)                          |
| <b>AXL</b>       | Accelerometer type            | AXL:0                             |
| <b>OBD</b>       | Displays OBD chip ID          | OBD:0                             |
| <b>BL</b>        | Bootloader version            | BL:1.6                            |
| <b>BT</b>        | Bluetooth® version            | BT:4                              |