

Frequency Bands

[Main Page](#) > [Frequently Asked Questions - FAQ](#) > **Frequency Bands**

This page contains a list of frequency bands supported by different Teltonika Telematics products.

□

Contents

- [1 FMB001](#)
- [2 FMB002](#)
- [3 FMB003](#)
- [4 FMB010](#)
- [5 FMB020](#)
- [6 FMB110](#)
- [7 FMB120](#)
- [8 FMB122](#)
- [9 FMB125](#)
- [10 FMB130](#)
- [11 FMB140](#)
- [12 FMB202](#)
- [13 FMB204](#)
- [14 FMB209](#)
- [15 FMB225](#)
- [16 FMB230](#)
- [17 FMB240](#)
- [18 FMB900](#)
- [19 FMB910](#)
- [20 FMB920](#)
- [21 FMB965](#)
- [22 FMT100](#)
- [23 MSP500](#)
- [24 MTB100](#)
- [25 FMP100](#)
- [26 FMB640](#)
- [27 FMB641](#)
- [28 FMC00A](#)
- [29 FMC001](#)
- [30 FMC003](#)
- [31 FMC225](#)
- [32 FMC230](#)
- [33 FMC920](#)
- [34 FMC125](#)
- [35 FMC130](#)
- [36 FMC640](#)
- [37 FMM00A](#)
- [38 FMM001](#)

- [39 FMM003](#)
- [40 FMM125](#)
- [41 FMM130](#)
- [42 FMM230](#)
- [43 FMM920](#)
- [44 FMM640](#)

FMB001

Product code	Region (operator)	Module name	Supported bands
FMB001 SD****	World Wide market	• TM2500	• 2G: B2 (1900 Mhz), B3 (1800 MHz), B5 (850 Mhz) B8 (900 MHz)

FMB002

Product code	Region (operator)	Module name	Supported bands
FMB002 Z1****	World Wide market	• TM2500	• 2G: B2 (1900 Mhz), B3 (1800 MHz), B5 (850 Mhz) B8 (900 MHz)

FMB003

Product code	Region (operator)	Module name	Supported bands
FMB003 77****	World Wide market	• TM2500	• 2G: B2 (1900 Mhz), B3 (1800 MHz), B5 (850 Mhz) B8 (900 MHz)

FMB010

Product code	Region (operator)	Module name	Supported bands
FMB010 H0****	World Wide market	• TM2500	• 2G: B2 (1900 Mhz), B3 (1800 MHz), B5 (850 Mhz) B8 (900 MHz)

FMB020

Product code	Region (operator)	Module name	Supported bands
FMB020 4M****	World Wide market	• TM2500	• 2G: B2 (1900 Mhz), B3 (1800 MHz), B5 (850 Mhz) B8 (900 MHz)

FMB110

Product code	Region (operator)	Module name	Supported bands
FMB110 BB****	World Wide market	• TM2500	• 2G: B2 (1900 Mhz), B3 (1800 MHz), B5 (850 Mhz) B8 (900 MHz)

FMB120

Product code	Region (operator)	Module name	Supported bands
FMB120 B6****	World Wide market	• TM2500	• 2G: B2 (1900 Mhz), B3 (1800 MHz), B5 (850 Mhz) B8 (900 MHz)

FMB122

Product code	Region (operator)	Module name	Supported bands
FMB122 BI****	World Wide market	• TM2500	• 2G: B2 (1900 Mhz), B3 (1800 MHz), B5 (850 Mhz) B8 (900 MHz)

FMB125

Product code	Region (operator)	Module name	Supported bands
FMB125 BJ****	World Wide market	• TM2500	• 2G: B2 (1900 Mhz), B3 (1800 MHz), B5 (850 Mhz) B8 (900 MHz)

FMB130

Product code	Region (operator)	Module name	Supported bands
FMB130 BS****	World Wide market	• TM2500	• 2G: B2 (1900 Mhz), B3 (1800 MHz), B5 (850 Mhz) B8 (900 MHz)

FMB140

Product code	Region (operator)	Module name	Supported bands
FMB140 BT****	World Wide market	• TM2500	• 2G: B2 (1900 Mhz), B3 (1800 MHz), B5 (850 Mhz) B8 (900 MHz)

FMB202

Product code	Region (operator)	Module name	Supported bands
FMB202 BC****	World Wide market	• TM2500	• 2G: B2 (1900 Mhz), B3 (1800 MHz), B5 (850 Mhz) B8 (900 MHz)

FMB204

Product code	Region (operator)	Module name	Supported bands
FMB204 BD****	World Wide market	• TM2500	• 2G: B2 (1900 Mhz), B3 (1800 MHz), B5 (850 Mhz) B8 (900 MHz)

FMB209

Product code	Region (operator)	Module name	Supported bands
FMB209 55****	World Wide market	• TM2500	• 2G: B2 (1900 Mhz), B3 (1800 MHz), B5 (850 Mhz) B8 (900 MHz)

FMB225

Product code	Region (operator)	Module name	Supported bands
FMB225 BR****	World Wide market	• TM2500	• 2G: B2 (1900 Mhz), B3 (1800 MHz), B5 (850 Mhz) B8 (900 MHz)

FMB230

Product code	Region (operator)	Module name	Supported bands
FMB230 BS****	World Wide market	• TM2500	• 2G: B2 (1900 Mhz), B3 (1800 MHz), B5 (850 Mhz) B8 (900 MHz)

FMB240

Product code	Region (operator)	Module name	Supported bands
FMB240 BT****	World Wide market	• TM2500	• 2G: B2 (1900 Mhz), B3 (1800 MHz), B5 (850 Mhz) B8 (900 MHz)

FMB900

Product code	Region (operator)	Module name	Supported bands
FMB900 AG****	World Wide market	• TM2500	• 2G: B2 (1900 Mhz), B3 (1800 MHz), B5 (850 Mhz) B8 (900 MHz)

FMB910

Product code	Region (operator)	Module name	Supported bands
FMB910 93****	World Wide market	• TM2500	• 2G: B2 (1900 Mhz), B3 (1800 MHz), B5 (850 Mhz) B8 (900 MHz)

FMB920

Product code	Region (operator)	Module name	Supported bands
FMB920 AE****	World Wide market	• TM2500	• 2G: B2 (1900 Mhz), B3 (1800 MHz), B5 (850 Mhz) B8 (900 MHz)

FMB965

Product code	Region (operator)	Module name	Supported bands
FMB965 3E****	World Wide market	• TM2500	• 2G: B2 (1900 Mhz), B3 (1800 MHz), B5 (850 Mhz) B8 (900 MHz)

FMT100

Product code	Region (operator)	Module name	Supported bands
FMT100 1A****	World Wide market	• TM2500	• 2G: B2 (1900 Mhz), B3 (1800 MHz), B5 (850 Mhz) B8 (900 MHz)

MSP500

Product code	Region (operator)	Module name	Supported bands
MSP500 CQ****	World Wide market	• TM2500	• 2G: B2 (1900 Mhz), B3 (1800 MHz), B5 (850 Mhz) B8 (900 MHz)

MTB100

Product code	Region (operator)	Module name	Supported bands
MTB100 93****	World Wide market	• TM2500	• 2G: B2 (1900 Mhz), B3 (1800 MHz), B5 (850 Mhz) B8 (900 MHz)

FMP100

Product code	Region (operator)	Module name	Supported bands
FMP100 UE****	World Wide market	• TM2500	• 2G: B2 (1900 Mhz), B3 (1800 MHz), B5 (850 Mhz) B8 (900 MHz)

FMB640

Product code	Region (operator)	Module name	Supported bands
FMB640 3B****	World Wide market	• TM2500	• 2G: B2 (1900 Mhz), B3 (1800 MHz), B5 (850 Mhz) B8 (900 MHz)

FMB641

Product code	Region (operator)	Module name	Supported bands
FMB641 NX****	World Wide market	• TM2500	• 2G: B2 (1900 Mhz), B3 (1800 MHz), B5 (850 Mhz) B8 (900 MHz)

FMC00A

Product code	Region (operator)	Module name	Supported bands
FMC00A 3D****	World Wide market	• Quectel EG91-NA, TM2500	• 4G (LTE-FDD): B2 (1900 Mhz), B4 (1700 MHz), B5 (850 Mhz), B12 (700 MHz), B13 (700 Mhz) • 2G: B2 (1900 MHz), B3 (1800 MHz), B5 (850 MHz), B8 (900 MHz)

FMC001

Product code	Region (operator)	Module name	Supported bands
FMC001 86****	World Wide market	• Quectel EG91-EX	• 4G (LTE-FDD): B1 (2100 MHz), B3 (1800 MHz), B7 (2600 MHz), B8 (900 MHz), B20 (800 MHz), B28A (700 MHz) • 3G: B1 (2100 MHz), B8 (900 MHz) • 2G: B3 (1800 MHz), B8 (900 MHz)

FMC003

Product code	Region (operator)	Module name	Supported bands
FMC003 X4****	EU, MEA.	• MeiG SLM320-PE2C (jamming)	• 4G (LTE-FDD): B1 (2100 MHz), B3 (1800 MHz), B7 (2600 MHz), B8 (900 MHz), B20 (800 Mhz), B28 (700 MHz) • 4G (LTE-TDD): B38 (2600 Mhz), B40 (2300 MHz), B41 (2500 Mhz) • 2G: B2 (1900 MHz), B3 (1800 MHz), B5 (850 MHz), B8 (900 MHz)

FMC003 WM****	APAC, LATAM.	<ul style="list-style-type: none"> • MeiG SLM320-L16A (jamming) 	<ul style="list-style-type: none"> • 4G (LTE-FDD): B1 (2100 MHz), B2 (1900 MHz), B3 (1800 MHz), B4 (1700 Mhz), B5 (850 MHz), B7 (2600 MHz), B8 (900 MHz), B20 (800 MHz), B28 (700 MHz) • 4G (LTE-TDD): B40 (2300 MHz) • 2G: B2 (1900 Mhz), B3 (1800 MHz), B5 (850 MHz), B8 (900 MHz)
----------------------	--------------	--	--

FMC225

Product code	Region (operator)	Module name	Supported bands
FMC225 83****	EU, MEA.	<ul style="list-style-type: none"> • MeiG SLM320-PE2C (jamming) 	<ul style="list-style-type: none"> • 4G (LTE-FDD): B1 (2100 MHz), B3 (1800 MHz), B7 (2600 MHz), B8 (900 MHz), B20 (800 Mhz), B28 (700 MHz) • 4G (LTE-TDD): B38 (2600 Mhz), B40 (2300 MHz), B41 (2500 Mhz) • 2G: B2 (1900 MHz), B3 (1800 MHz), B5 (850 MHz), B8 (900 MHz)
FMC225 F3****	APAC, LATAM.	<ul style="list-style-type: none"> • MeiG SLM320-L16A (jamming) 	<ul style="list-style-type: none"> • 4G (LTE-FDD): B1 (2100 MHz), B2 (1900 MHz), B3 (1800 MHz), B4 (1700 Mhz), B5 (850 MHz), B7 (2600 MHz), B8 (900 MHz), B20 (800 MHz), B28 (700 MHz) • 4G (LTE-TDD): B40 (2300 MHz) • 2G: B2 (1900 Mhz), B3 (1800 MHz), B5 (850 MHz), B8 (900 MHz)

FMC230

Product code	Region (operator)	Module name	Supported bands
FMC230 KY****	EU, MEA.	<ul style="list-style-type: none"> • MeiG SLM320-PE2C (jamming) 	<ul style="list-style-type: none"> • 4G (LTE-FDD): B1 (2100 MHz), B3 (1800 MHz), B7 (2600 MHz), B8 (900 MHz), B20 (800 Mhz), B28 (700 MHz) • 4G (LTE-TDD): B38 (2600 Mhz), B40 (2300 MHz), B41 (2500 Mhz) • 2G: B2 (1900 MHz), B3 (1800 MHz), B5 (850 MHz), B8 (900 MHz)
FMC230 40****	APAC, LATAM.	<ul style="list-style-type: none"> • MeiG SLM320-L16A (jamming) 	<ul style="list-style-type: none"> • 4G (LTE-FDD): B1 (2100 MHz), B2 (1900 MHz), B3 (1800 MHz), B4 (1700 Mhz), B5 (850 MHz), B7 (2600 MHz), B8 (900 MHz), B20 (800 MHz), B28 (700 MHz) • 4G (LTE-TDD): B40 (2300 MHz) • 2G: B2 (1900 Mhz), B3 (1800 MHz), B5 (850 MHz), B8 (900 MHz)

FMC920

Product code	Region (operator)	Module name	Supported bands
FMC920 LO****	EU, MEA, APAC.	<ul style="list-style-type: none"> • Quectel EG915U-EU, TM2500. 	<ul style="list-style-type: none"> • 4G (LTE-FDD): B1 (2100 MHz), B3 (1800 MHz), B7 (2600 MHz), B8 (900 MHz), B20 (800 Mhz), B28 (700 MHz) • 2G: B2 (1900 MHz), B3 (1800 MHz), B5 (850 MHz), B8 (900 MHz)
FMC920 O2****	LATAM.	<ul style="list-style-type: none"> • EG915U-LA 	<ul style="list-style-type: none"> • 4G (LTE-FDD): B2 (1900 MHz), B3 (1800 MHz), B4 (1700 Mhz), B5 (850 MHz), B7 (2600 MHz), B8 (900 MHz), B20 (800 MHz), B28 (700 MHz), B66 (1700 Mhz) • 2G: B2 (1900 Mhz), B3 (1800 MHz), B5 (850 MHz), B8 (900 MHz)

FMC125

Product code	Region (operator)	Module name	Supported bands
FMC125 TL****	EU, MEA	<ul style="list-style-type: none"> • MeiG SLM320-PE2C (jamming detection), TM2500 	<ul style="list-style-type: none"> • 4G (LTE-FDD): B1 (2100 MHz), B3 (1800 MHz), B7 (2600 MHz), B8 (900 MHz), B20 (800 MHz), B28 (700 MHz) • 4G (LTE-TDD): B38 (2600 MHz), B40 (2300 MHz), B41 (2500 MHz) • 2G: B2 (1900 MHz), B3 (1800 MHz), B5 (850 MHz), B8 (900 MHz)
FMC125 47****	APAC, LATAM	<ul style="list-style-type: none"> • MeiG SLM320-L16A (jamming detection), TM2500 	<ul style="list-style-type: none"> • 4G (LTE-FDD): B1 (2100 MHz), B2 (1900 MHz), B3 (1800 MHz), B4 (1700 MHz), B5 (850 MHz), B7 (2600 MHz), B8 (900 MHz), B20 (800 MHz), B28 (700 MHz) • 4G (LTE-TDD): B40 (2300 MHz) • 2G: B3 (1800 MHz), B8 (900 MHz)

FMC130

Product code	Region (operator)	Module name	Supported bands
FMC130 8H****	EU, MEA	<ul style="list-style-type: none"> • MeiG SLM320-PE1A (jamming detection), TM2500 	<ul style="list-style-type: none"> • 4G (LTE-FDD): B1 (2100 MHz), B3 (1800 MHz), B5 (850 MHz), B7 (2600 MHz), B8 (900 MHz), B20 (800 MHz) • 4G (LTE-TDD): B38 (2600 MHz), B40 (2300 MHz), B41 (2500 MHz) • 2G: B2 (1900 MHz), B3 (1800 MHz), B5 (850 MHz), B8 (900 MHz)
FMC130 KY****	EU, MEA	<ul style="list-style-type: none"> • MeiG SLM320-PE2C (jamming detection), TM2500 	<ul style="list-style-type: none"> • 4G (LTE-FDD): B1 (2100 MHz), B3 (1800 MHz), B7 (2600 MHz), B8 (900 MHz), B20 (800 MHz), B28(700 MHz) • 4G (LTE-TDD): B38 (2600 MHz), B40 (2300 MHz), B41 (2500 MHz) • 2G: B2 (1900 MHz), B3 (1800 MHz), B5 (850 MHz), B8 (900 MHz)
FMC130 40****	APAC, LATAM	<ul style="list-style-type: none"> • MeiG SLM320-L16A (jamming detection), TM2500 	<ul style="list-style-type: none"> • 4G (LTE-FDD): B1 (2100 MHz), B2 (1900 MHz), B3 (1800 MHz), B4 (1700 MHz), B5 (850 MHz), B7 (2600 MHz), B8 (900 MHz), B20 (800 MHz), B28(700 MHz) • 4G (LTE-TDD): B40 (2300 MHz) • 2G: B2 (1900 MHz), B3 (1800 MHz), B5 (850 MHz), B8 (900 MHz)

FMC640

Product code	Region (operator)	Module name	Supported bands
FMC640 UX****	Latin America/Australia & New Zealand market	• Quectel EG91-AUX	<ul style="list-style-type: none">• 4G (LTE-FDD): B1 (2100 MHz), B2 (1900 MHz), B3 (1800 MHz), B4 (1700 MHz), B5 (850 MHz), B7 (2600 MHz), B8 (900 MHz), B28 (700 MHz), B66 (1700/2100 MHz)• 3G: B1 (2100 MHz), B2 (1900 MHz), B5 (850 MHz), B8 (900 MHz)• 2G: B2 (1900 MHz), B3 (1800 MHz), B5 (850 MHz), B8 (900 MHz)
FMC640 25****	EMEA market	• Quectel EG91-EX	<ul style="list-style-type: none">• 4G (LTE-FDD): B1 (2100 MHz), B3 (1800 MHz), B7 (2600 MHz), B8 (900 MHz), B20 (800 MHz), B28 (700 MHz)• 3G: B1 (2100 MHz), B8 (900 MHz)• 2G: B3 (1800 MHz), B8 (900 MHz)

FMM00A

Product code	Region (operator)	Module name	Supported bands
FMM00A 1K****	World Wide market	• BG95-M1, TM2500	<ul style="list-style-type: none">• 4G (LTE-FDD): B1 (2100 Mhz),B2 (1900 Mhz),B3 (1800 Mhz),B4 (1700 Mhz),B5 (850 Mhz),B8 (900 Mhz),B12 (700 Mhz),B13 (700 Mhz),B18 (850 Mhz),B19 (850 Mhz),B20 (800 Mhz),B25 (1900 Mhz),B26 (850 Mhz),B27 (850 Mhz),B28 (700 Mhz),B66 (1700 Mhz),B85 (700 Mhz)• 2G: B2 (1900 MHz), B3 (1800 MHz), B5 (850 MHz), B8 (900 MHz)

FMM001

Product code	Region (operator)	Module name	Supported bands
FMM001 CC****	World Wide market	• Quectel BG95-M3, TM2500	<ul style="list-style-type: none">• 4G (LTE-FDD): B1 (2100 MHz), B2 (1900 MHz), B3 (1800 MHz), B4 (1700 MHz), B5 (850 MHz), B8 (900 MHz), B12 (700 MHz), B13 (700 MHz), B18 (850 MHz), B19 (800 MHz), B20 (800 MHz), B25 (1900 MHz), B26 (850 MHz), B27 (850 MHz), B28 (700 MHz), B66 (1700 MHz), B85 (700 MHz)• 4G (LTE-TDD): B1 (2100 MHz), B2 (1900 MHz), B3 (1800 MHz), B4 (1700 MHz), B5 (850 MHz), B8 (900 MHz), B12 (700 MHz), B13 (700 MHz), B18 (850 MHz), B19 (800 MHz), B20 (800 MHz), B25 (1900 MHz), B28 (700 MHz), B66 (1700 MHz), B71 (600 MHz), B85 (700 MHz)• 2G: B2 (1900 MHz), B3 (1800 MHz), B5 (850 MHz), B8 (900 MHz)

FMM003

Product code	Region (operator)	Module name	Supported bands
FMM003 7F****	World Wide market	• BG95-M3, TM2500	<ul style="list-style-type: none">• 4G (LTE-FDD): B1 (2100 MHz), B2 (1900 MHz), B3 (1800 MHz), B4 (1700 MHz), B5 (850 MHz), B8 (900 MHz), B12 (700 MHz), B13 (700 MHz), B18 (850 MHz), B19 (800 MHz), B20 (800 MHz), B25 (1900 MHz), B26 (850 MHz), B27 (850 MHz), B28 (700 MHz) B66 (1700 MHz), B85 (700 MHz)• 4G (LTE-TDD): B1 (2100 MHz), B2 (1900 MHz), B3 (1800 MHz), B4 (1700 MHz), B5 (850 MHz), B8 (900 MHz), B12 (700 MHz), B13 (700 MHz), B18 (850 MHz), B19 (800 MHz), B20 (800 MHz), B25 (1900 MHz), B28 (700 MHz) B66 (1700 MHz), B71 (600 MHz), B85 (700 MHz)• 2G: B2 (1900 MHz), B3 (1800 MHz), B5 (850 MHz), B8 (900 MHz)

FMM125

Product code	Region (operator)	Module name	Supported bands
FMM125 7V****	World Wide market	• Quectel BG96, TM2500	<ul style="list-style-type: none">• 4G (LTE-FDD): B1 (2100 MHz), B2 (1900 MHz), B3 (1800 MHz), B4 (1700 MHz), B5 (850 MHz), B8 (900 MHz), B12 (700 MHz), B13 (700 MHz), B18 (850 MHz), B19 (800 MHz), B20 (800 MHz), B28 (700 MHz)• 4G (LTE-TDD): B39 (1900 MHz) (for CAT-M1 only)• 2G: B2 (1900 MHz), B3 (1800 MHz), B5 (850 MHz), B8 (900 MHz)

FMM130

Product code	Region (operator)	Module name	Supported bands
FMM130 6V****	World Wide market	• Quectel BG96	<ul style="list-style-type: none">• 4G (LTE-FDD) (CAT M1): B1 (2100 MHz), B2 (1900 MHz), B3 (1800 MHz), B4 (1700 MHz), B5 (850 MHz), B8 (900 MHz), B12 (700 MHz), B13 (700 MHz), B18 (850 MHz), B19 (800 MHz), B20 (800 MHz), B28 (700 MHz)• 4G (LTE-TDD): B39 (1900 MHz) (for CAT-M1 only)• 2G: B2 (1900 MHz), B3 (1800 MHz), B5 (850 MHz), B8 (900 MHz)

FMM130 LN****	World Wide market	• Quectel BG95-M3	<ul style="list-style-type: none"> • 4G (LTE-FDD) (CAT M1): B1 (2100 MHz), B2 (1900 MHz), B3 (1800 MHz), B4 (1700 MHz), B5 (850 MHz), B8 (900 MHz), B12 (700 MHz), B13 (700 MHz), B18 (850 MHz), B19 (800 MHz), B20 (800 MHz), B25 (1900 MHz), B26 (850 MHz), B27 (850 MHz), B28 (700 MHz), B66 (1700 MHz), B85 (700 MHz) • 4G (LTE-FDD) (CAT NB2): B1 (2100 MHz), B2 (1900 MHz), B3 (1800 MHz), B4 (1700 MHz), B5 (850 MHz), B8 (900 MHz), B12 (700 MHz), B13 (700 MHz), B18 (850 MHz), B19 (800 MHz), B20 (800 MHz), B25 (1900 MHz), B28 (700 MHz), B66 (1700 MHz), B71 (600 MHz), B85 (700 MHz) • 2G: B2 (1900 MHz), B3 (1800 MHz), B5 (850 MHz), B8 (900 MHz)
---------------	-------------------	-------------------	---

FMM230

Product code	Region (operator)	Module name	Supported bands
FMM230 LN****	World Wide market	• Quectel BG95-M3, TM2500	<ul style="list-style-type: none"> • 4G (LTE-FDD): B1 (2100 MHz), B2 (1900 MHz), B3 (1800 MHz), B4 (1700 MHz), B5 (850 MHz), B8 (900 MHz), B12 (700 MHz), B13 (700 MHz), B18 (850 MHz), B19 (800 MHz), B20 (800 MHz), B25 (1900 MHz), B26 (850 MHz), B27 (850 MHz), B28 (700 MHz) B66 (1700 MHz), B85 (700 MHz) • 4G (LTE-TDD): B1 (2100 MHz), B2 (1900 MHz), B3 (1800 MHz), B4 (1700 MHz), B5 (850 MHz), B8 (900 MHz), B12 (700 MHz), B13 (700 MHz), B18 (850 MHz), B19 (800 MHz), B20 (800 MHz), B25 (1900 MHz), B28 (700 MHz) B66 (1700 MHz), B71 (600 MHz), B85 (700 MHz) • 2G: B2 (1900 MHz), B3 (1800 MHz), B5 (850 MHz), B8 (900 MHz)

FMM920

Product code	Region (operator)	Module name	Supported bands
FMM920 34****	World Wide market	• Quectel BG95-M3, TM2500	<ul style="list-style-type: none"> • 4G (LTE-FDD): B1 (2100 MHz), B2 (1900 MHz), B3 (1800 MHz), B4 (1700 MHz), B5 (850 MHz), B8 (900 MHz), B12 (700 MHz), B13 (700 MHz), B18 (850 MHz), B19 (800 MHz), B20 (800 MHz), B25 (1900 MHz), B26 (850 MHz), B27 (850 MHz), B28 (700 MHz) B66 (1700 MHz), B85 (700 MHz) • 4G (LTE-TDD): B1 (2100 MHz), B2 (1900 MHz), B3 (1800 MHz), B4 (1700 MHz), B5 (850 MHz), B8 (900 MHz), B12 (700 MHz), B13 (700 MHz), B18 (850 MHz), B19 (800 MHz), B20 (800 MHz), B25 (1900 MHz), B28 (700 MHz) B66 (1700 MHz), B71 (600 MHz), B85 (700 MHz) • 2G: B2 (1900 MHz), B3 (1800 MHz), B5 (850 MHz), B8 (900 MHz)

FMM640

Product code	Region (operator)	Module name	Supported bands
FMM640 XJ****	World Wide market	• Quectel BG96	<ul style="list-style-type: none"> • 4G (LTE-FDD): B1 (2100 MHz), B2 (1900 MHz), B3 (1800 MHz), B4 (1700 MHz), B5 (850 MHz), B8 (900 MHz), B12 (700 MHz), B13 (700 MHz), B18 (850 MHz), B19 (800 MHz), B20 (800 MHz), B26 (850 MHz), B28 (700 MHz) • 4G (LTE-TDD): B39 (1900 MHz) (for CAT-M1 only) • 2G: B2 (1900 MHz), B3 (1800 MHz), B5 (850 MHz), B8 (900 MHz)