

# Template:FM36M1 Electrical characteristics

## Electrical characteristics

| Characteristic description                                       | Value |        |                |      |
|--|-------|--------|----------------|------|
|  | Min.  | Typ.   | Max.           | Unit |
| <b>Supply Voltage:</b>   |       |        |                |      |
| <b>Supply Voltage (Recommended Operating Conditions)</b>         | 10    |        | 30             | V    |
| <b>Drain current (Digital Output1 OFF)</b>                       |       | 241.69 |                | μA   |
| <b>Drain current (Digital Output1 ON)</b>                        | 0.1   |        | 0.5            | A    |
| <b>Drain current (Digital Output2 OFF)</b>                       |       | 240.26 |                | μA   |
| <b>Drain current (Digital Output2 ON)</b>                        | 0.1   |        | 0.5            | A    |
| <b>Static Drain-Source resistance (Digital Output ON)</b>        |       |        | 300            | mΩ   |
| <b>Digital Input:</b>  |       |        |                |      |
| <b>Input resistance (DIN1)</b>                                   | 15    |        |                | kΩ   |
| <b>Input resistance (DIN2, AIN2)</b>                             | 20    |        |                | kΩ   |
| <b>Input resistance (AIN1)</b>                                   | 120   |        |                | kΩ   |
| <b>Input voltage (Recommended Operating Conditions)</b>          | 0     |        | Supply voltage | V    |
| <b>Input Voltage threshold (DIN1)</b>                            |       | 7.5    |                | V    |
| <b>Input Voltage threshold (DIN2)</b>                            |       | 2.5    |                | V    |
| <b>Input Voltage threshold (AIN1, AIN2)</b>                      |       | 3.5    |                | V    |
| <b>Analog Input:</b>   |       |        |                |      |
| <b>Input voltage (Recommended Operating Conditions), Range 1</b> | 0     |        | 10             | V    |
| <b>Input resistance, Range 1</b>                                 |       | 120    |                | kΩ   |
| <b>Measurement error</b>   |       | 0.47   |                | %    |
| <b>Additional error</b>  |       | ±17.3  |                | mV   |
| <b>Input Voltage (Recommended Operating Conditions), Range 2</b> | 0     |        | 30             | V    |
| <b>Input resistance, Range 2</b>                                 |       | 150    |                | kΩ   |
| <b>Measurement error</b>   |       | 1.01   |                | %    |
| <b>Additional error</b>  |       | ±139   | 0              | mV   |

✘ Analog Input error margin can increase if temperature varies.