

# FMP100 LED status

[Main Page](#) > [Fast & Easy Trackers](#) > [FMP100](#) > [FMP100 Manual](#) > **FMP100 LED status**

□

## Contents

- [1 Package contents](#)
- [2 GSM indication](#)
- [3 GNSS indication](#)
- [4 Event indication](#)

## Package contents



- The FMP100 device have predefined **LED** and **buzzer** indication set out of the box. To better understand device indications, in this page will be explained device behavior.

## GSM indication



- When device doesn't obtain GSM signal, after every 300 seconds period, for the 0.5 second three times will light up RED light and buzzer will make sound simultaneously.

## GNSS indication



- When device doesn't obtain GNSS signal, after every 60 seconds period, for the 1 second will light up RED light.
- When device have GNSS signal, after every 60 seconds period, for the 1 second will light up GREEN light.

## Event indication



- When FMP100 button is pressed, you will hear an audio notification for the 1 second to confirm button click was registered.
- Private mode will be indicated with GREEN light, which will blink three times for 0.5 second.
- Business mode will be indicated with BLUE light, which will blink three times for 0.5 second.