

Template:FM36 LV CAN Features

Parameter ID	Default value	Value range		Value	Parameter name
		Min	Max		
1620	0	0	2	0 - Auto Detect 1 - LV-CAN200 2 - High 3 - ALL-CAN300	CAN Mode
1621	0	0	1	0 - Disable 1 - Enable	Send data with 0, if ignition is off