

Template:FM36 System Parameters

Parameter ID	Parameter Type	Default value	Value range		Value	Parameter name
			Min	Max		
1000	U8	0	0	2	0 - Disabled 1 - GPS Sleep 2 - Deep Sleep	Sleep Settings
200	U8	1	1	3000	-	Sleep Timeout
1001	U8	0	0	1	0 - 10V 1 - 30V	Analog Input value range
1002	U8	1	0	3	0 - ignition 1 - Msensor 2 - GPS 3 - ignition + Msensor	Stop Detection Source
1003	U8	0	0	1	0 - Disabled 1 - Enabled	Static Navigation
1004		0	0	2	0 - Power voltage 1 - Digital input 1 2 - Msensor	Ignition Source
1005		30000 mV	13000 mV	30000 mV		High Voltage Level
1006		13000 mV	0	30000 mV		Low Voltage Level
1008		0	0	1	0 - Manual 1 - Automatic	Ignition Detection
1009	U8	10	0	65535		Ignition Detection Timeout
1007	U8	60	0	65535		GNSS FIX Timeout for Time Synchronization via NTP
201	U8	0	0	1	0 - Disabled 1 - Enabled	Saving/Sending without time synchronization
202	U8	0	0	2	0 - GNSS (all available) 1 - GPS 2 - GLONASS	Satellite System